Product data sheet Characteristics

9001KR3BH13 PUSH BUTTON 600VAC 10A 30MM T-K

Product availability: Stock - Normally stocked in distribution facility



| Main | |
|---------------------------------|------------------|
| Range of product | Harmony 9001K |
| Product or component type | Push-button |
| Device short name | К |
| Type of operator | Spring return |
| Operator profile | Black projecting |
| Operator additional information | Without guard |

Complementary

| Bezel material | Chromium plated metal |
|--------------------------------|------------------------------|
| Mounting diameter | 1.18 in (30 mm) |
| Light source | Without |
| Light source | Without |
| Light block supply | Without supply |
| Contacts type and composition | 1 C/O |
| Connections - terminals | Screw clamp terminals |
| Operating position | Any position |
| [le] rated operational current | 10 A (AC-15) 10 A (DC-13) |
| Contact operation | Standard |
| Device presentation | Complete product |

Environment

| Product certifications | CE NEMA UL listed file E42259 CCN NKCR CSA LR 25490 class 3211 03 |
|---------------------------|--|
| NEMA degree of protection | NEMA 1/2/3/3R/4/6/12/13 |

Ordering and shipping details

| Category | 21426 - 9001 K (NOT KA,KM,KX) | |
|-----------------------|-------------------------------|--|
| Discount Schedule | CS1 | |
| GTIN | 00785901851967 | |
| Nbr. of units in pkg. | 1 | |
| Package weight(Lbs) | 0.2800000000000003 | |
| Returnability | Υ | |
| Country of origin | MX | |

Offer Sustainability

| RoHS (date code: YYWW) | Compliant - since 0921 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity | |
|---------------------------|--|--|
| REACh | Reference not containing SVHC above the threshold | |
| California proposition 65 | WARNING: This product can expose you to chemicals including: | |
| Substance 1 | Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. | |
| More information | For more information go to www.p65warnings.ca.gov | |

| Warranty period | 18 months |
|-----------------|-----------|

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Pushbutton Switches category:

Click to view products by Schneider manufacturer:

Other Similar products are found below:

8940K2012 LW1L-M1C10V-A LW1L-M1C70-A LW2L-A1C20M-GD LW2L-M1C20M-A 60324L M22-D-R-GB0/K11 M7E-HRN2
67021K512 67081K512X 701PB580 7199K101 810K12910 810KSV30B MML21EA2ADK MML21KA3ABK MML23KA3AC05K-001
MML23KW3AA01W 8418K2 8442K3 8450K1 860K11911T01A 861901 861K11911T01A07 861K13810T00A14 861K13911
8646AB6X718UL 8646ABUL 9001KXRK 907AYY100 PMHD155A1 9533CD4+U574+U4922 95-414.000 99-450.837 99-453.837
PV3H2B0NN-341 1203MRA A22NZBGANGA A22NZBNANGA A22NZMPATRA A2PMA1X03EC56 A3A-5123-02 A3A-7140 A3A-7310 A3A-7340 A3U-TMW-A2C-5M A595 12037A2ULCSA ABD122N-B 1211390004