


**Schneider Electric Relays**

 200 N. Martingale Rd., Suite 1000  
 Schaumburg, IL 60173


Phone: 847-441-2540 • Fax: 847-881-0741

 E-Mail: [relays@schneider-electric.com](mailto:relays@schneider-electric.com) • Web site: [www.serelays.com](http://www.serelays.com)

ALL CATEGORIES &gt; 976 SERIES RELAYS &gt; ITEM # 976XBXH-240A

ITEM # 976XBXH-240A, SLIM-LINE PCB RELAY / DPDT, 5 AMP RATED

Less than 1 cubic inch



## Specifications

Status	Standard
Check Inventory	<a href="#">Check Distributor Inventory</a>
Contact Configuration	DPDT
Nominal Input Voltage	240 VAC 50/60 Hz
Coil Resistance (Ohms)	22000 Ohm
Current Rating	5 A
Contact Materials	Silver Alloy
Switching Voltage (AC, Resistive)	5 A at 240 VAC 50/60 Hz
Switching Voltage (DC, Resistive)	5 A at 30 VDC
Operating Range - % of Nominal (DC)	85 to 110 %
Average Consumption (AC / VA)	1.20 VA
Average Consumption (DC / W)	0.53 W
Drop-out Voltage Threshold (AC)	30 %
Drop-out Voltage Threshold (DC)	10 %
Electrical Life, Operations at Rated Current (Resistive)	100000
Mechanical Life, Unpowered	10000000
Operating Time (Response Time)	15 ms
Dielectric Strength - Between Poles (AC)	1000 V(rms) 5000 V(rms)
Vibration Resistance - Operational	3 g-n at 10-55 Hz
Shock Resistance	10 g-n

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [General Purpose Relays](#) category:*

*Click to view products by [Schneider](#) manufacturer:*

Other Similar products are found below :

[PCN-105D3MH,000](#) [59641F200](#) [LY1SAC110120](#) [5X827E](#) [5X837F](#) [5X840F](#) [5X842F](#) [5X848E](#) [LY2N-AC120](#) [LY2S-AC220/240](#) [LY2-US-AC120](#) [LY3-US-AC120](#) [LY4F-UA-DC12](#) [LY4F-UA-DC24](#) [LY4F-US-AC120](#) [LY4F-US-AC240](#) [LY4F-US-DC24](#) [LY4F-VD-AC110](#) [LYQ20DC12](#) [M115C60](#) [M115N010](#) [M115N0150](#) [6031007G](#) [603-12D](#) [61211T0B4](#) [61212T400](#) [61222Q400](#) [61243B600](#) [61243C500](#) [61243Q400](#) [61311BOA2](#) [61311BOA6](#) [61311BOA8](#) [61311C0A2](#) [61311COA1](#) [61311COA6](#) [61311F0A2](#) [61311QOA1](#) [61311QOA4](#) [61311T0D6](#) [61311TOA6](#) [61311TOA7](#) [61311TOB3](#) [61311TOB4](#) [61311U0A6](#) [61312Q600](#) [61312T400](#) [61312T600](#) [61313U200](#) [61313U400](#)