

Product data sheet

Specifications



cartridge M200 - 2 analog voltage outputs

TMCR2AQ2V

Main

Range of product	Easy Modicon M200
Product or component type	Analogue output cartridge
Product compatibility	Easy Modicon M200

Complementary

Analogue output number	2
Analogue output type	Voltage: 0...10 V
Analogue output resolution	12 bits
LSB value	2.44 mV 0...10 V voltage
Load type	Resistive
Load impedance ohmic	≥ 2 kOhm
Conversion time	20 ms
Stabilisation time	40 ms
Absolute accuracy error	+/- 1 % of full scale +/- 0.3 % of full scale at 25 °C
Temperature drift	+/- 0.02 %FS/°C
Repeat accuracy	+/- 0.4 %FS
Non-linearity	+/- 0.01 %FS
Cross talk	≤ 1 LSB
Type of cable	Twisted shielded pairs cable
Electrical connection	3 x 1.5 mm ² 2 screw terminal blocks with pitch 3.81 mm adjustment for outputs
Maximum cable distance between devices	Twisted shielded pairs cable: <30 m for output
Insulation	Non-insulated between analogue output and internal logic
Height	41 mm
Depth	15 mm
Width	35 mm
Net weight	0.012 kg

Environment

Immunity to microbreaks	10 ms
-------------------------	-------

Packing Units

Unit Type of Package 1	PCE
------------------------	-----

Number of Units in Package 1	1
------------------------------	---

Package 1 Height	4.6 cm
------------------	--------

Package 1 Width	7.0 cm
-----------------	--------

Package 1 Length	3.5 cm
------------------	--------

Package 1 Weight	20.0 g
------------------	--------

Unit Type of Package 2	S02
------------------------	-----

Number of Units in Package 2	75
------------------------------	----

Package 2 Height	15 cm
------------------	-------

Package 2 Width	30 cm
-----------------	-------

Package 2 Length	40 cm
------------------	-------

Package 2 Weight	3.07 kg
------------------	---------

Unit Type of Package 3	P06
------------------------	-----

Number of Units in Package 3	1200
------------------------------	------

Package 3 Height	75 cm
------------------	-------

Package 3 Width	60 cm
-----------------	-------

Package 3 Length	80 cm
------------------	-------

Package 3 Weight	106 kg
------------------	--------

Offer Sustainability

REACH Regulation	REACH Declaration
------------------	-----------------------------------

EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration
-------------------	---

Toxic heavy metal free	Yes
------------------------	-----

Mercury free	Yes
--------------	-----

China RoHS Regulation	China RoHS declaration
-----------------------	--

RoHS exemption information	Yes
----------------------------	-----

California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
---------------------------	---

Recommended replacement(s)

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [PLC Controllers](#) category:

Click to view products by [Schneider](#) manufacturer:

Other Similar products are found below :

[3G2A5PS223E](#) [CJ1M-CPU13](#) [CS1W-CN227](#) [CP1H-Y20DT-D](#) [AFP0RDA4](#) [FC6A-C16R1AE](#) [TM200CE24T](#) [TM200C24R](#) [TMCR2AQ2V](#)
[TM200C40T](#) [TM200C40R](#) [TM200CE32R](#) [EASY-BOX-E4-AC1](#) [TMCR2AM3](#) [TM200CE24R](#) [TM200C16T](#) [TM200C24T](#) [6GK1901-1BB30-0AA0](#) [6ES7193-6BP00-0DA1](#) [6ES7155-6AR00-0AN0](#) [6ES7193-6BP40-0DA1](#) [6ES7972-0BB12-0XA0](#) [6ES7193-6BP40-0BA1](#) [6ES7193-6PA00-0AA0](#) [6ES7972-0BB52-0XA0](#) [6ES7135-6GB00-0BA1](#) [6ES7134-6FF00-0AA1](#) [6ES7132-6BD20-0BA0](#) [6ES7131-6BF01-2BA0](#)
[6ES7522-1BL10-0AA0](#) [6ES7134-6JF00-0CA1](#) [6ES7193-6BP20-0BF0](#) [6ES7521-1BL10-0AA0](#) [6ES7226-6RA32-0XB0](#) [6ES7132-6HD01-0BB1](#) [6ES7193-6BP20-0BB1](#) [6ES7590-1AE80-0AA0](#) [6ES7226-6DA32-0XB0](#) [6ES7392-1AJ00-0AA0](#) [6ES7972-0BA12-0XA0](#) [6ES7522-1BL01-0AB0](#) [6ES7226-6BA32-0XB0](#) [CPM2C10CDT1MD](#) [AFP0RC14RS](#) [2906916](#) [2906920](#) [2906921](#) [CJ2M-MD211](#) [CS1W-OA201](#)
[CJ2M-MD212](#)