


## VW3A3502

multi-pump card - 24 V DC - 9-way male SUB-D connector - for Altivar speed drive



### Main

Product or component type	Multi-pump card
Range compatibility	Altivar 61 Altivar 61Q
[Us] rated supply voltage	24 V
Supply circuit type	DC
Analogue input number	2
Analogue input type	AI51, AI52 current analog input : 0...20 mA, impedance: 250 Ohm, resolution: 10 bits
Analogue output number	2
Analogue output type	AO51, AO52 current analog output : 0...20 mA, impedance: 500 Ohm, resolution: 10 bits
Discrete input number	10
Discrete input type	(LI51...LI60) logic inputs, 24 V DC, compatible with level 1 PLC (voltage limits: <= 30 V), impedance: 4.4 kOhm
Discrete input logic	(LI51...LI60) positive state 0 <= 5 V state 1 >= 11 V
Discrete output number	6
Discrete output type	(LO51...LO56) logic output, compatible with level 1 PLC
Discrete output logic	(LO51...LO56) positive
Battery type	Lithium

### Complementary

Connector type	9-way male SUB-D connector
Supply voltage limits	19...30 V
Current consumption	2 A maximum 200 mA maximum per logic output 80 mA no load
Discrete output voltage	24 V DC, maximum switching voltage: 30 V logic output
Maximum output current	0.2 A, logic output
Electrical connection	Terminal, 1.5 mm <sup>2</sup> / AWG 16, 0.25 N.m
Battery life	8 yr
Product weight	0.32 kg

### Environment

### Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Schneider manufacturer](#):*

Other Similar products are found below :

[ZA2BV05](#) [RE22R2MMW](#) [RE22R2MYMR](#) [67SPCX-56](#) [70-454](#) [70S2-01-A-03-V](#) [70S2-05-B-12-S](#) [712XBXC-240A](#) [7S](#) [MMS124](#)  
[8501NR45](#) [8501NR51](#) [8501NR52](#) [8501RSD41V53](#) [861HSSR410-AC-1](#) [9001KP35LRR9](#) [9001KS11BH13](#) [9007MA18](#) [9007MS10S0300](#)  
[9013FHG39J69](#) [11HPX-75](#) [A283BXX69C-48D](#) [A283XAXC-24A](#) [GZ1E02](#) [ABL8WPS24200](#) [ATS01N212LU](#) [16-711C4](#) [16-782FT-1](#)  
[IIHPX-75](#) [RPM12B7](#) [9001KR1BH13](#) [9001KR1GH5](#) [9001KR1UH5](#) [9001KR9R](#) [9001KS46BH2](#) [9001SKS11BH2](#) [9007MS02S0054](#)  
[9007MS05S0300](#) [9013FRG2J70](#) [9013FSG2J15](#) [RTX-132 24/48 120SEK](#) [RTX-132 24/48 1,2SEK](#) [RTX-133 110/127 12SEK](#) [RTX-170 24/48](#)  
[LC1K0610F7](#) [283XAXC-24A](#) [SM552A100](#) [SM956A130000](#) [SM956A132600](#) [SR2B201FU](#)