

Product availability: Non-Stock - Not normally stocked in distribution facility



Main

Range	TeSys
Product or component type	Contactor coil
Range compatibility	TeSys LC1B contactor TeSys CR1B contactor
Control circuit type	DC AC
Coil type	Low consumption
[Uc] control circuit voltage	110...125 V DC 120...127 V AC 50...400 Hz

Complementary


Control circuit voltage limits	69...79 V
Average resistance	11.4 Ohm
Inrush power in VA	1100...1300 VA 3P 1300...1600 VA 4P 450...620 VA 1P 720...1000 VA 2P
Inrush power in W	1100...1400 W for 4P 380...520 W for 1P 600...800 W for 2P 900...1100 W for 3P
Hold-in power consumption in VA	0.15...0.2 VA 50...400 Hz 1P 0.35...0.5 VA 50...400 Hz 2P 0.7...1 VA 50...400 Hz 3P 1.2...1.6 VA 50...400 Hz 4P
Hold-in power consumption in W	0.15...0.2 W for 1P 0.35...0.5 W for 2P 0.7...1 W for 3P 1.2...1.6 W for 4P
Operating time	25 ms sealed
Mechanical durability	1200000 cycles
Operating rate	<= 120 cyc/mn at <= 131 °F (55 °C)
Product weight	2.47 lb(US) (1.12 kg)

Ordering and shipping details

Category	18074 - SPARE PARTS DISCOUNT I11
Discount Schedule	I11
GTIN	003389110479409
Nbr. of units in pkg.	1
Package weight(Lbs)	2.4900000000000002
Returnability	N
Country of origin	FR

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Offer Sustainability

RoHS (date code: YYWW)	Compliant - since 0801 - Schneider Electric declaration of conformity  Schneider Electric declaration of conformity
REACH	Reference not containing SVHC above the threshold
California proposition 65	WARNING: This product can expose you to chemicals including:
----- Substance 1	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
----- More information	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Contactor Accessories](#) category:

Click to view products by [Schneider](#) manufacturer:

Other Similar products are found below :

[3RT1945-5AP61](#) [SZ-N2SJ](#) [YC9Z-CI6](#) [CA5-22M](#) [EHTK210](#) [MS325-SM1](#) [13222574](#) [SW182B-1](#) [SW190B-24DC-CW4](#) [SZ-CD1](#) [SZ-N8J](#)
[SZ-ZM1E](#) [YC9Z-CNA111SR](#) [YC9Z-CUA422](#) [DPEAN11](#) [3RH1911-1GA40](#) [3RH29111GA22](#) [3RT1924-5AC21](#) [3RT1924-5AK61](#) [3RT1935-](#)
[5AP61](#) [3RT1944-5AC21](#) [3RT1944-5AP61](#) [3RT1945-5AC21](#) [3TY6483-0AK6](#) [CA7-PA-01](#) [CA7-PA-10](#) [CA7-PA-11](#) [CA7-PV-S22](#) [CA7-S9](#)
[B88269X2200C101](#) [CAL5-11](#) [DB25/25A](#) [DB42](#) [DB80](#) [LDC4](#) [SZ-A11](#)