


SCHUKO socket strip



Part no.: 60110-202

Features:

- Socket strip with 9 SCHUKO socket inserts
- Mounting height 1 U, 19" mounting dimension
- Connection lead 2 m with SCHUKO / UTE connector / plug
- For installation sockets can be turned in all four directions (in 90° increments)
- Assembly horizontal and vertical possible
- 230 V, 16 A
- According to DIN 41494, DIN 57620, VDE 0620



Technical information:

Description	Socket inserts	Height	Length	Length	Depth
SCHUKO - Standard without functional element, 19"	9	1 U	19" Inch	438.5 mm	44 mm

Downloads:

[data sheet \(PDF\)](#) ([Log in](#) Required)

[Customised socket strips](#)

To gain access to the additional information you must [Log in](#).
If you do not yet have a user name, you may [Register here](#).

Delivery comprises: assembled

Item	Qty	Description
1	1	Al extrusion, 1 U, anodised, for socket inserts
2	9	SCHUKO socket inserts (35° rotated, PA, RAL 7035)
3	2	Endpiece, PA, RAL 7035
4	1	Connecting cable, black, 2 m, 05VV-F 3G 1.5 mm ² , with SCHUKO/UTE plug, PVC, encapsulated
5	2	Mounting angle, PA, RAL 7035

Accessories:

Part no.	Description	
21101-809	19" assembly kit (screw, washer, nut) (50 × M6 x 16 screws, 50 × plastic washers, 50 × cage nuts)	Add to basket

20110-068	Mounting bracket for socket strips for vertical mounting, St, 2 mm, PU 2 pieces	Add to basket
21190-435	19" assembly kit (screw, washer, nut) (32 x M6 screws x 16, 32 x plastic washers, 32 x cage nuts)	Add to basket
21101-810	19" assembly kit (screw, washer, nut) (100 x M6 x 16 screws, 100 x plastic washers, 100 x cage nuts)	Add to basket
21190-095	19" assembly kit (screw, washer, nut) (4 x M6 screws x 16, 4 x plastic washers, 4 x cage nuts)	Add to basket

Note:

- Please order mounting bracket for vertical assembly separately

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [schroff](#) manufacturer:

Other Similar products are found below :

[24566-125](#) [14575271](#) [14576145](#) [14575265](#) [20117-156](#) [20817772](#) [20827088](#) [20846211](#) [20860229](#) [21100777](#) [23130082](#) [24571331](#) [24571586](#)
[24572066](#) [26230-374](#) [30825080](#) [20849021](#) [20860240](#) [23001021](#) [24560080](#) [24571303](#) [24572054](#) [24572056](#) [30219-113](#) [20848-410](#) [20838-125](#) [20860-605](#) [10225-602](#) [10225-623](#) [10828058](#) [13100103](#) [13100123](#) [28230-439-C](#) [24563-457](#) [24563-444](#) [20848-601](#) [21101-853](#) [24563-133](#) [24563-134](#) [24564-431](#) [24827-107](#) [24563-142](#) [24563-157](#) [24563-442](#) [A265HC-5.80EH](#) [24561-331](#) [10225640](#) [10225696](#) [16230005](#)
[16230007](#)