

Rating	
16A 125V AC	1/3HP 125V AC
10A 250V AC	1/2HP 250V AC
Contact resistance	
50mΩ Max	
Insulation resistance	
DC 500V 100MΩ Min	
Dielectric strength	
AC 1500V 1 minute	
Cut-out	
X	Y

FEATURES

- * MATERIAL: Frame is nylon (UL flame: 94V-2). Terminals are silver plated brass.
- * Illuminated actuators are molded in PC, available with red, amber, green, blue and white colors.
- * Snap-in mounting, easy to install switch into panel.
- * Waterproof cover is optional.
- * The only difference between R13-66B and R13-66B6 is the rocker style.



Actuator	X	Y
0.75-1.25	18.0±1	13.0±1
1.25-2	18.4±1	13.0±1
2-3	18.8±1	13.0±1

Cut-out for X8 ROCKER

Actuator	X	Y
0.75-1.25	18.4±1	13.0±1
1.5-2.5	18.8±1	13.0±1



Ordering number instruction

R13-66 - [] - []

FUNCTION

Different button (按鈕不同)



Illuminated / Different button (帶燈/按鈕不同)




Momentary / Illuminated / Different button (彈回/帶燈/按鈕不同)



Different position / Different button (動作特性不同/按鈕不同)



Momentary / Different button (彈回/按鈕不同)



Independent circuit / Different button (獨立迴路/按鈕不同)



Waterproof (防水)



TERMINAL

0 2	187° SQ
0 5	SO
0 9	PC
1 0	PC ANGLE
1 2	SO

ROCKER

A/B/BF/C/D/E/F	G/H/I
B, BF transparent	
A5	
B, BF transparent	
B2/B2F	
L/B4/BF4	
AP/CP/DP/HP/IP	
B6/B6F	
B6, B6F transparent	
A8/B8/B8F/C8	F8

X-ON Electronics

Largest Supplier of
Electrical and
Electronic
Components

*Click to view
similar products
for [Rocker Switches](#)
category:*

*Click to view
products by [SCI](#)
manufacturer:*

Other Similar
products are found
below :

[VKD2GHNB-](#)

[00000-000](#)

[VSD2GNNB-](#)

[00000-000](#)

7036WWCDBX65

3+U622

7747NAB+U627/1

8055K52Z7V

8138K20E6M50

FMC12A2200005

FMC18A2200002

FML18A276A000

84206L 84312LX

PREDD4-07F-

BB0FW

PREDD5-07F-

BB0GW 999-

16702-001

A101J2ZQ004

A101J4ZQ004

A101J51CB0004

A107J51ZQ0004

A201J1AQ004

A201J1AV2Q004

A201J3ZB004

A201J50ZQ004

A203J51ZQ0004

A226L11YZQ

A22L11A

A435S1YZQ

H8500XBBBBBL-

A

HB130CHNWWN

AAC 1251.0303

AE205J60V3B004

RH110C2NBB

1352.0107

1363.0201

AML23GBE2AA0

5

AML25GBF2AA0

3GR

B123J77V7B2

B226J50W4Q22P

B433J37ZQ22M

160212E

1801.1164

1831.1102

1833.3402

1837.1118

1838.8302

1839.1502

K1ABBSCADN

K2ABAAAAAA

RSCA211-VB-B-

9-V 2600R21E

2631LH/2A21200

0L0

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Rocker Switches](#) category:

Click to view products by [SCI manufacturer](#):

Other Similar products are found below :

[VKD2GHNB-00000-000](#) [VSD2GNNB-00000-000](#) [6-1571986-5](#) [6-1571986-9](#) [7036WWCDBX653+U622](#) [8055K52Z7V](#) [8138K20E6M50](#)
[FMC18A2200002](#) [84206L](#) [84312LX](#) [PREDD4-07F-BB0FW](#) [PREDD5-07F-BB0GW](#) [PRFDD1-16F-BB000](#) [PRFDD3-16F-BB000](#) [1-](#)
[1634201-0](#) [999-16702-001](#) [A101J2ZQ004](#) [A101J4ZQ004](#) [A101J51CB0004](#) [A107J51ZQ0004](#) [A201J1AQ004](#) [A201J1AV2Q004](#)
[A201J3ZB004](#) [A201J50ZQ004](#) [A203J51ZQ0004](#) [A226L11YZQ](#) [A22L11A](#) [A435S1YZQ](#) [H8500XBBBBL-A](#) [H8653VBBG2577W](#)
[HB130CHNWWNAAC](#) [1251.0303](#) [AE205J60V3B004](#) [RH110C2NBB](#) [1352.0107](#) [1363.0201](#) [AML25GBF2AA03GR](#) [1571099-3](#) [1571987-4](#)
[1571987-5](#) [1571989-7](#) [B123J77V7B2](#) [B226J50W4Q22P](#) [B433J37ZQ22M](#) [160212E](#) [1801.1164](#) [1831.1102](#) [1833.3402](#) [1837.1118](#) [1838.8302](#)