


LL914...LL4454

Silicon Epitaxial Planar Switching Diode

for general purpose and switching.


LL-34



Glass case MiniMELF
Dimensions in mm

Maximum Ratings and Electrical Characteristics

Type	Peak Reverse Voltage	Aver. Rectified Current	Power Dissip. at 25 °C	Junction Temperature	Forward Voltage		Reverse Current		Reverse Recovery Time	
	V _{RM}	I _{F(AV)}	P _{tot}	T _j	V _F	at I _F	I _R	at V _R	t _{rr}	Conditions
	(V)	Max.(mA)	(mW)	(°C)	Max.(V)	(mA)	Max.(nA)	(V)	Max.(ns)	
LL914	100	75	500	200	1	10	25	20	4	I _F = 10 mA, V _R = 6 V, R _L = 100 Ω, to I _R = 1 mA
LL4149	100	150	500	200	1	10	25	20	4	I _F = 10 mA, V _R = 6 V, R _L = 100 Ω, to I _R = 1 mA
LL4152	40	150	400	175	0.55	0.1	50	30	2	I _F = 10 mA, V _R = 6 V, R _L = 100 Ω, to I _R = 1 mA
LL4154	35	150	500	200	1	30	100	25	2	I _F = 10 mA, V _R = 6 V, R _L = 100 Ω, to I _R = 1 mA
LL4447	100	150	500	200	1	20	25	20	4	I _F = 10 mA, V _R = 6 V, R _L = 100 Ω, to I _R = 1 mA
LL4449	100	150	500	200	1	30	25	20	4	I _F = 10 mA, V _R = 6 V, R _L = 100 Ω, to I _R = 1 mA
LL4450	40	150	400	175	0.54	0.5	50	30	4	I _F = I _R = 10 mA, to I _R = 1 mA
LL4451	40	150	400	175	0.5	0.1	50	30	10	I _F = I _R = 10 mA, to I _R = 1 mA
LL4453	30	150	400	175	0.55	0.01	50	20	-	-
LL4454	75	150	400	175	1	10	100	50	4	I _F = I _R = 10 mA, to I _R = 1 mA



SEMTECH ELECTRONICS LTD.
Subsidiary of Sino-Tech International (BVI) Limited



Dated : 12/08/2010 Rev:01

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Diodes - General Purpose, Power, Switching category:

Click to view products by Semtech manufacturer:

Other Similar products are found below :

[MMBD3004S-13-F](#) [RD0306T-H](#) [DSE010-TR-E](#) [BAV17-TR](#) [BAV19-TR](#) [1N3611](#) [NTE156A](#) [NTE574](#) [NTE6244](#) [1SS181-TP](#) [1SS193,LF](#)
[1SS400CST2RA](#) [SDAA13](#) [SHN2D02FUTW1T1G](#) [LS4151GS08](#) [FC903-TR-E](#) [1N4449](#) [1N456A](#) [1N4934-E3/73](#) [1N914B](#) [1N914BTR](#)
[1SS226-TP](#) [RFUH20TB3S](#) [D291S45T](#) [BAV300-TR](#) [BAW56DWQ-7-F](#) [BAW75-TAP](#) [MM230L-CAA](#) [IDW40E65D1](#) [JAN1N3600](#) [LL4151-GS18](#) [053684A](#) [SMMSD4148T3G](#) [707803H](#) [NSVDAN222T1G](#) [CDSZC01100-HF](#) [LL4150-M-08](#) [BAV199E6433HTMA1](#) [BAS28-7](#)
[BAW56HDW-13](#) [BAS28 TR](#) [VS-HFA04SD60STR-M3](#) [NSVM1MA152WKT1G](#) [RGP30D-E3/73](#) [BAV99TQ-13-F](#) [BAS21DWA-7](#) [NTE6250](#)
[NTE582-4](#) [NTE582-6](#) [MMDB30-E28X](#)