




SIMATIC ET 200SP, Potential distributor module, PotDis terminal block, PotDis-TB-P1-R, 18 x potential P1, Push-In terminals Packaging Unit: 1 Piece,

General information	
Product type designation	PotDis TB P1-R, PU 1
HW functional status	FS10 and higher
Color code for module-specific color identification plate	CC12
Supply voltage	
Rated value (DC)	
• For P1 and P2 bus	48 V; max.
• for process terminals	48 V; max.
external protection for power supply lines	Yes; 10 A miniature circuit breaker with type B or C tripping characteristic for the respective rated supply voltage
Current carrying capacity	
up to 60 °C, max.	10 A
For P1 and P2 bus, max.	10 A
For process terminals, max.	10 A
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	-30 °C
• horizontal installation, max.	60 °C
• vertical installation, min.	-30 °C
• vertical installation, max.	50 °C
Altitude during operation relating to sea level	
• Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Accessories	
Color coding labels	
• for process terminals	CC10, CC12
connection method	
Terminals	
• Terminal type	Push-in terminal
• Conductor cross-section, min.	0.14 mm <sup>2</sup> ; 0.2 mm <sup>2</sup> without wire end ferrule
• Conductor cross-section, max.	2.5 mm <sup>2</sup> ; 1.5 mm <sup>2</sup> with wire end ferrule
• Number of process terminals to I/O module	16
• Number of terminals to AUX bus	0
• Number of add-on terminals	0
• Number of terminals with connection to P1 and P2 bus	2
Dimensions	
Width	15 mm
Height	74 mm
Depth	34 mm
Weights	
Weight, approx.	24 g

---

last modified:

8/27/2023 

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [PLC Controllers](#) category:*

*Click to view products by [Siemens](#) manufacturer:*

Other Similar products are found below :

[3G2A5PS223E](#) [CJ1M-CPU13](#) [CS1W-CN227](#) [CP1H-Y20DT-D](#) [AFP0RDA4](#) [FC6A-C16R1AE](#) [EASY-E4-AC-12RCX1P](#) [EASY-E4-AC-16RE1P](#) [EASY-E4-AC-8RE1P](#) [EASY-E4-DC-12TC1P](#) [EASY-E4-DC-16TE1P](#) [EASY-E4-DC-4PE1P](#) [EASY-E4-DC-6AE1P](#) [EASY-E4-DC-8TE1P](#) [EASY-E4-UC-12RC1P](#) [EASY-E4-UC-12RCX1P](#) [EASY-E4-UC-16RE1P](#) [EASY-E4-UC-8RE1P](#) [TM200CE24T](#) [TM200C24R](#) [TMCR2AQ2V](#) [TM200C40T](#) [TM200C40R](#) [TM200CE32R](#) [EASY-BOX-E4-AC1](#) [TMCR2AM3](#) [TM200CE24R](#) [TM200C16T](#) [TM200C24T](#) [6GK1901-1BB30-0AA0](#) [6ES7193-6BP00-0DA1](#) [6ES7155-6AR00-0AN0](#) [6ES7193-6BP40-0DA1](#) [6ES7972-0BB12-0XA0](#) [6ES7511-1AK02-0AB0](#) [6ES7193-6BP40-0BA1](#) [6ES7193-6PA00-0AA0](#) [6ES7972-0BB52-0XA0](#) [6ES7135-6GB00-0BA1](#) [6ED1052-2HB08-0BA2](#) [6ES7134-6FF00-0AA1](#) [6ES7132-6BD20-0BA0](#) [6ES7131-6BF01-2BA0](#) [6ES7522-1BL10-0AA0](#) [6ES7134-6JF00-0CA1](#) [6ES7193-6BP20-0BF0](#) [6ES7521-1BL10-0AA0](#) [6EP7133-6AB00-0BN0](#) [6ES7226-6RA32-0XB0](#) [6ES7132-6HD01-0BB1](#)