



SIMATIC ET 200SP, Potential distributor module, PotDis-BaseUnit PotDis-BU Typ P2, light-colored, 1 x P1-potential, 17 x P2-potential, Push-In terminals. P1-, P2- and AUX-rail disconnected from left BU, Packaging Unit: 1 Piece, WxH: 15mm x 117mm

General information	
Product type designation	PotDis BU type P2, light version, PU 1
HW functional status	FS10 and higher
Color code for module-specific color identification plate	CC63
Supply voltage	
Rated value (DC)	
• For P1 and P2 bus	48 V; max.
• for process terminals	48 V; max.
external protection for power supply lines	Yes; 10 A miniature circuit breaker with type B or C tripping characteristic for the respective rated supply voltage
Current carrying capacity	
For P1 and P2 bus, max.	10 A
For process terminals, max.	10 A
Hardware configuration	
Formation of potential groups	
• New potential group	No
• Potential group continued from the left	Yes
Slots	
• Number of slots	1
Potential separation	
between backplane bus and supply voltage	Yes
Isolation	
Isolation tested with	3 250 V DC
Ambient conditions	
Ambient temperature during operation	
• horizontal installation, min.	-30 °C
• horizontal installation, max.	60 °C
• vertical installation, min.	-30 °C
• vertical installation, max.	50 °C
Altitude during operation relating to sea level	
• Installation altitude above sea level, max.	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Accessories	
Color coding labels	
• for process terminals	CC63
connection method	
Terminals	
• Terminal type	Push-in terminal
• Conductor cross-section, min.	0.14 mm ²
• Conductor cross-section, max.	2.5 mm ²
• Number of terminals with connection to P1 and P2 bus	18; 17 terminals to P2, 1 terminal to P1

Dimensions	
Width	15 mm
Height	117 mm
Depth	35 mm
Weights	
Weight, approx.	40 g

last modified: 8/27/2023 

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [PLC Controllers](#) category:

Click to view products by [Siemens](#) manufacturer:

Other Similar products are found below :

[3G2A5PS223E](#) [CJ1M-CPU13](#) [CS1W-CN227](#) [CP1H-Y20DT-D](#) [AFP0RDA4](#) [FC6A-C16R1AE](#) [TM200CE24T](#) [TM200C24R](#) [TMCR2AQ2V](#)
[TM200C40T](#) [TM200C40R](#) [TM200CE32R](#) [EASY-BOX-E4-AC1](#) [TMCR2AM3](#) [TM200CE24R](#) [TM200C16T](#) [TM200C24T](#) [6GK1901-1BB30-0AA0](#) [6ES7193-6BP00-0DA1](#) [6ES7155-6AR00-0AN0](#) [6ES7193-6BP40-0DA1](#) [6ES7972-0BB12-0XA0](#) [6ES7511-1AK02-0AB0](#) [6ES7193-6BP40-0BA1](#) [6ES7193-6PA00-0AA0](#) [6ES7972-0BB52-0XA0](#) [6ES7135-6GB00-0BA1](#) [6ES7134-6FF00-0AA1](#) [6ES7132-6BD20-0BA0](#) [6ES7131-6BF01-2BA0](#) [6ES7522-1BL10-0AA0](#) [6ES7134-6JF00-0CA1](#) [6ES7193-6BP20-0BF0](#) [6ES7521-1BL10-0AA0](#) [6ES7226-6RA32-0XB0](#) [6ES7132-6HD01-0BB1](#) [6ES7193-6BP20-0BB1](#) [6ES7590-1AE80-0AA0](#) [6ES7226-6DA32-0XB0](#) [6ES7392-1AJ00-0AA0](#) [6ES7972-0BA12-0XA0](#) [6ES7522-1BL01-0AB0](#) [6ES7226-6BA32-0XB0](#) [6ES7137-6AA01-0BA0](#) [6ES7392-1AM00-0AA0](#) [6ES7972-0BB42-0XA0](#) [6ES7193-6BP20-0BA0](#) [6ES7131-6BF01-0BA0](#) [6ES7392-1BM01-0AA0](#) [6ES7193-6BP20-0DA0](#)