



Control Power Transformer, 200va, PRI 240x480 230x460 220 440v, SEC 120/115/110v, Domestic,

product brand name	Control Power Transformer
design of the product	Control power voltage
special product feature	Robust design
General technical data	
weight [lb]	8.5 lb
Height x Width x Depth [in]	4.46 × 4.5 × 4.37 in
ambient temperature [°F] during operation	-4 ... +104 °F
ambient temperature during operation	-20 ... +40 °C
country of origin	Mexico
operating apparent power rated value	200 VA
Enclosure	
design of the housing	Open
Mounting/wiring	
mounting position	Any
fastening method	Surface mounting
type of electrical connection at output for main current circuit	Screw-type terminals (touchsafe)
type of electrical connection at input for main current circuit	Screw-type terminals (touchsafe)
Inputs/ Outputs	
input variables of primary voltage	240x480,230x460,220x440vac
output dimensions of secondary voltage	120/115/110vac
phase number of the inputs	1
electrical input frequency	50 ... 60 Hz
input voltage _1	240 V
input voltage _2	480 V
input voltage _3	230 V
input voltage _4	460 V
input voltage _5	220 V
input voltage _6	440 V
phase number of the outputs	1
electrical output frequency	60 ... 50 Hz
output voltage _1 rated value	120 V
output voltage _3 rated value	110 V
output voltage _2 rated value	115 V
certificate of suitability	UL / CSA
Further information	

Industrial Controls - Product Overview (Catalogs, Brochures,...)

www.usa.siemens.com/iccatalog

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/us/Catalog/product?mlfb=US2:MT0200A>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/US/en/ps/US2:MT0200A>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=US2:MT0200A&lang=en
Certificates/approvals
<https://support.industry.siemens.com/cs/US/en/ps/US2:MT0200A/certificate>

last modified:

5/31/2021 

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Power Transformers](#) category:

Click to view products by [Siemens](#) manufacturer:

Other Similar products are found below :

[0505 1W](#) [063929](#) [063932](#) [063934](#) [093830](#) [094929](#) [094931](#) [094932](#) [10-12](#) [10A009](#) [11328-T060](#) [11328-T073](#) [11328-T074](#) [1-1611449-0](#) [1-1611760-0](#) [1182D240](#) [1182E110](#) [1182E117](#) [1182F240](#) [1182F30](#) [1182G117](#) [1182G22](#) [1182H18](#) [1182J117](#) [1182J15](#) [1182J18](#) [1182K117](#) [1182K12](#) [1182K6](#) [1182L12](#) [1182L18](#) [1182L22](#) [1182L240](#) [1182L30](#) [1182L6](#) [1182L60](#) [1182M110](#) [1182M117](#) [1182M12](#) [1182M15](#) [1182M18](#) [1182M22](#) [1182M30](#) [1182M9](#) [1182N117](#) [1182N22](#) [1182N6](#) [1182N60](#) [1182N9](#) [1182P117](#)