




GNSS Antenna Module



SIM33ELA

SIMCom presents a high performance GPS module accompany with GNSS antenna-SIM33ELA. This is a standalone GNSS module embedded a linear antenna . Designed with MTK's high sensitivity navigation engine, it allows you to achieves the industry's highest levels of sensitivity, accuracy, and Time-to-First-Fix (TTFF) with lowest power consumption. And with embedded antenna in SMT type, it is very easy to embed into customer's application.

Smart Machine Smart Decision

Mechanical data

- Dimensions: 14*9.6*2.15mm
- Weight: 0.5g

Features

- Support GPS/GLONASS/Galileo/QZSS
- Support EASY™ self-generated orbit prediction
- Support EPO™ orbit prediction
- Support AGPS
- Support SBAS ranging (WAAS, EGNOS, GAGAN, MSAS)
- Support Jamming Removing
- Low-noise amplifier has been integrated

Interfaces

- | | |
|--------------------|-----------|
| •Serial interfaces | UART |
| •Digital I/O | PPS |
| | 3D-FIX |
| | FORCE -ON |
| •Protocols | NMEA |
| | PMTK |

Support product

- SIM68 EVB KIT with USB V2.0 full speed interface

Performance data

- | | |
|-----------------------------------|---|
| •Receiver type | 33tracking/99 acquisition-channel GNSS receiver |
| •Max. update rate | 10Hz |
| •Sensitivity ¹ | |
| Tracking: | -165 dBm |
| Reacquisition: | -160 dBm |
| Cold starts: | -147 dBm |
| •Time-To-First-Fix ² | |
| Cold starts: | 28 s (typical) |
| Warm starts: | 26s |
| Hot starts: | <1s |
| EPO Assist: | 13s (CTTFF) |
| •Accuracy | |
| Automatic Position ³ : | 2.5m CEP |
| Speed ⁴ : | 0.1m/s |
| •Operation temperature: | -40°C~+85 °C |

Electrical data

- | | |
|---------------------------------|----------------|
| •Power supply | 2.8~4.3V |
| •Backup power | 2.0V~4.3V |
| •Power consumption ² | 3.3V (typical) |
| Acquisition | 25mA |
| Tracking | 20mA |
| Backup | 14uA |

1.Demonstrated on EVB KIT at library

2.All SV @ -130 dBm

3.50% 24 hr static, -130dBm

4.50%@ 30m/s

More about SIMCom SIM33ELA
Please contact:
Tel: 86-21-32523300
Fax: 86-21-32523301
Email: simcom@sim.com
Website: www.sim.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for GPS Modules category:

Click to view products by Simcom manufacturer:

Other Similar products are found below :

[A5135-H](#) [EWM-G109H01E](#) [ISM3333-C6.1](#) [S2-106ZN](#) [S2-105V4-Z185K](#) [MIKROE-4150](#) [GPS-11858](#) [4037735104327](#) [RXM-GNSS-TM-T](#)
[EWM-G108H01E](#) [DD-14239](#) [GPS-10922](#) [GPS-12751](#) [NEO-M8P-2](#) [SIM28ML](#) [RXM-GNSS-GM-T](#) [SIM28](#) [M10578-A3](#) [M10578-A3-U2](#)
[TEL0132](#) [POL-2G](#) [POL-3G](#) [FT-X-GPS](#) [GPS-13740](#) [PKG300060P](#) [PKG300071](#) [PKG300071P](#) [PKG900000000271T](#) [PKG90000000853P](#)
[PKG90000000853T](#) [EZ-GPS-G](#) [A2235H](#) [RXM-GNSS-TM-B](#) [RXM-GPS-F4-T](#) [RXM-GPS-FM-B](#) [RXM-GPS-FM-T](#) [RXM-GPS-R4-T](#)
[A1084-A](#) [A2100-A](#) [A2200-A](#) [A2235-H](#) [A5100-A](#) [28504](#) [L26ADR-S89](#) [L26T-S89](#) [L89-S90](#) [101990655](#) [113990659](#) [GPS-13670](#) [TESEO-](#)
[LIV3F](#)