

LTE-FDD/LTE-TDD/HSPA+ GSM MODULE



SIM7100E



SIMCom presents an ultra compact and reliable wireless module SIM7100E which is based on Qualcomm MDM9215 multiple-mode LTE platform. SIM7100E is a complete multi-band TDD-LTE/FDD-LTE/WCDMA/GSM/GNSS SMT type module designed with very powerful processors integrating application core: Cortex™ A5(550MHz), three QDSP6 cores (Up to 500MHz), allowing customer to benefit from small dimensions and cost-effective product solutions.

It has strong extension capability with rich interfaces including UART, USB2.0, SPI, I2C, Keypad, PCM, etc. With abundant application capabilities like TCP/UDP/FTP/FTPS/HTTP/HTTPS/SMTP/POP3 and MMS, the module provides much flexibility and ease of integration for customer's applications.

Smart Machine Smart Decision

General features

- Five-Band FDD-LTE B1/B3/B7/B8/B20
- Dual-Band TDD-LTE B38/B40
- Dual-Band UMTS/HSDPA/HSPA+ B1/B8
- Dual-Band GSM/GPRS/EDGE 900/1800 MHz
- Control Via AT Commands
- Supply voltage range: 3.4V~ 4.2V
- Operation temperature: -40°C to +85°C
- Dimension: 30 X 30X 2.9 mm
- Weight: 5.8g
- GNSS: gpsOne Gen 8B;standalone;assisted,XTRA;

Specifications for Data transfer

- LTE
 - Uplink up to 50Mbps,
 - Downlink up to 100Mbps
- HSPA+
 - Uplink up to 5.76 Mbps,
 - Downlink up to 42 Mbps
- UMTS
 - Uplink/Downlink up to 384Kbps
- EDGE Class:
 - Max. 236.8Kbps(DL),Max. 236.8Kbps(UL)
- GPRS
 - Max. 85.6Kbps(DL), Max. 85.6Kbps(UL)
- CSD
 - GSM data rate 14.4Kbps
 - WCDMA data rate 57.6Kbps
 - WCDMA 64kbps CSD for Video call

Other features

- USB Driver for Microsoft Windows 2000/XP/Vista/7/8
- USB Driver for Windows CE/Mobile
- USB Driver for Linux /Android
- RIL supporting for Android/Windows CE/Mobile
- Automatic installation for windows
- Linux API SDK
- Firmware update via USB
- TCP/IP/IPV4/V6 Multi-PDP,MT PDP
- FTP/FTPS/HTTP/HTTPS/SMTP/POP3/DNS/MMS
- DTMF
- Gobi SDK to the Win7/Win8/Linux
- MBIM to Win8
- Source code of the PC manager of the device for reference

Interfaces

- USB2.0
- UART
- SIM card
- SPI
- I2C
- Keypad(5*5)
- Constant current sink
- GPIO
- ADC
- PCM *
- SDIO

Certifications

- CE (ongoing)
- ROHS
- REACH

NOTE: * Only supported in Home Security and Telematics Applications

More about SIMCom SIM7100E
Please contact:
Tel: 86-21-32523300
Fax: 86-21-32523301
Email: simcom@sim.com
Website: www.sim.com/wm

All specifications are subject to change without prior notice.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Modules](#) category:

Click to view products by [Simcom](#) manufacturer:

Other Similar products are found below :

[HMC-C009](#) [HMC-C011](#) [nRF24L01P-MODULE-PCB](#) [HMC-C021](#) [HMC-C024](#) [XB9XT-DPRS-721](#) [XBP9B-DMUTB022](#) [nRF24L01P-MODULE-SMA](#) [CMD-KEY2-418-CRE](#) [XM-C92-2P-UA](#) [XB9XT-DPUS-721](#) [V640-A90](#) [HMC-C583](#) [MAAM-008818-TR3000](#) [MTSMC-H5-U](#) [SIMSA868-PRO](#) [SIMSA915C-PRO](#) [SIMSA868C-PRO](#) [SIMSA433C-PRO](#) [SIMSA915-PRO](#) [XBP9B-DMUT-042](#) [HMC-C582](#) [HMC-C022](#) [XBP9B-DPST-041](#) [XBP9B-DMWT-042](#) [SM-MN-00-HF-RC](#) [HMC-C031](#) [MT-02](#) [M1002GB](#) [702-W](#) [SIMSA868C-N-PRO](#) [SIMSA433C-N-PRO](#) [SIMSA915C-N-PRO](#) [ADP-R202-00B](#) [PEPPER WIRELESS C1 USB](#) [S2-1050J-Z0K4J](#) [S2-10732-Z1T61](#) [S2-107XB-Z2356-Z2352](#) [S2-10672-Z1L85](#) [S2-10686-Z1L1D](#) [S2-10688-Z1L1T](#) [S2-106BA-Z1P20](#) [S2-1060C-Z1F0A](#) [S2-106R4-Z1Q6F-Z1Q6Q](#) [S2-106R4-Z1Q6J-Z1Q6Q](#) [S2-106R4-Z1Q67-Z1Q6Q](#) [S2-106RB-Z1Q6V-Z1Q6Q](#) [S2-107DR-Z1Y5B](#) [SU60-2230C-PU](#) [RC-TFSK3-868](#)