

欧式通用端子台

欧米式に通用できる端子台
European general terminal block



T022/T022-K



T023/T023-K



T024/T024-K

特点 Features

- * T022/T022-K为20P连接器对应20P端子连接, 可对应市面上所有带20P MIL插头的PLC连接。
- * T023/T023-K为34P连接器对应34P端子连接, 对应KEYENCE的KV-32XA/C, KV-64XA/C, KV-32TA/C, KV-64TA/C/扩展板使用。
- * T024/T024-K为40P连接器对应40P端子连接, 体积最小化设计。
- * T022/T022-K为20P的连接器对应20P端子连接, 市场中之全部の20P MILプラグのPLC接続に対応できます。
- * T023/T023-Kは34Pの连接器对应34P端子连接, KEYENCEのKV-32XA/C, KV-64XA/C, KV-32TA/C, KV-64TA/C/拡張板に对应使用します。
- * T024/T024-Kは40P连接器对应40P端子连接, 体積は最小型に設計します。
- * T022/T022-K is a 20pin terminal connection for 20pin connector, suitable to all PLC connections with 20pin MIL plug on the market.
- * T023/T023-K is a 34pin terminal connection for 34pin connector, applicable to KV-32XA/C, KV-64XA/C, KV-32TA/C and KV-64TA/C expansion modules of KEYENCE PLCs.
- * T024/T024-K is a 40pin terminal connection for 40pin connector, small size for space saving.

注意事項 note

- 订购前请确认好PLC引脚定义, 选择适合的端子台。
- 新PLC连接时, 请事先准备好与PLC引脚号对应的专用电缆。
- Before ordering, please confirm the PLC pin definition, choose the suitable terminal.
- When PLC connection, please be sure to use the company developed and the corresponding special cable.

适合电线 Suitable wire

1.5 mm² Following/ AWG16;
剥线长度: 6mm



选型参考 Type selection reference

型号 Model	T022	T022-K	T023	T023-K	T024	T024-K
名称 Name	欧式通用20位端子台		欧式通用34位端子台		欧式通用40位端子台	

适用PLC Suitable PLC

OMRON	C11W-M0232 C11W-M0233		C11W-D021 C11W-D022 C11W-D023 C11W-D024 C11W-M0230 C11W-M0231 C11W-M0232 C11W-M0233 C11W-M0234 C11W-M0235	C11W-D0222 C11W-D0223 C11W-D0224 C11W-D0225 C11W-M0230041 C11W-M0230042 C11W-M0231 C11W-M0232 C11W-M0233		
MITSUBISHI	FX1NC-16MT FX1NC-32MT FX2NC-16MT FX2NC-32MT FX2NC-16EX FX2NC-16EX-C	FX2NC-16EXL-C FX2NC-16EXY FX2NC-16EXY-C FX2N-16P FX2N-16M FX2N-20M	KV-32XA/C KV-64XA/C KV-32TA/C KV-64TA/C	KV-NC32T KV-NC32EX KV-NC32T KV-NC32EX	QX41 QX42 QX42-S1 QX11 QX72 QX19P	QX42P QY71 QX42P QD70P4 QD70P QD70D QD70M
KEYENCE	KV-NC18EX KV-NC18ET		KV-C32XA/C KV-D64XA/C KV-C32TA/C KV-D64TA/C	KV-NC32T KV-NC32EX KV-NC32T KV-NC32EX	KV-100 KV100E KV-300 KV300E KV-500	KV-S64PL KV-S64PL
Panasonic					FP0-XV40Z1P FP2-C1D FP2-C2D FP2-C3D FP2-C4D FP2-C5D FP2-C6D FP2-C7D FP2-C8D FP2-C9D FP2-C10D FP2-C11D FP2-C12D FP2-C13D FP2-C14D FP2-C15D FP2-C16D FP2-C17D FP2-C18D FP2-C19D FP2-C20D	FP0-XV40Z0P FP2-C1D FP2-C2D FP2-C3D FP2-C4D FP2-C5D FP2-C6D FP2-C7D FP2-C8D FP2-C9D FP2-C10D FP2-C11D FP2-C12D FP2-C13D FP2-C14D FP2-C15D FP2-C16D FP2-C17D FP2-C18D FP2-C19D FP2-C20D
SIEMENS					40P Plug with a full range	
Yokogawa					F3WD64-3N F3WD32-3F	F3WD64-3F F3WD32-3F

关联产品 Related products


通用电缆 Suitable cable	X200-2 X218-1 X218-9	X200-3 X210-3	X200-4 X210-4 X210-5 X218-6
	(详情请参阅本目录接线系列) For details, please refer to the directory cable series.		

规格参数 Specifications


输入 Input	额定电流 Nominal current 1A
额定电压 Nominal volt voltage	DC24V
输出侧对应 Corresponding output Devices	Servo motor control signal line circuit Button Switch, Photoelectric Switch, Solenoid, Indicator, Stepping Servo Motor, etc.

外形图 Dimensions


T022/T022-K



T023/T023-K



T024/T024-K




注: T022(T022-K)外形尺寸相同, T023(T023-K)外形尺寸相同。
Note: T022 and T022-K have the same shape size, T023 and T023-K have the same shape size.


- 用2个M4的螺丝可固定在零件安装的地方, 建议使用M4X1.6的螺丝, 螺孔深度3mm以上。
- 可安装在标准35mm的DIN导轨上。
- Screw Mounting: use M4*1.6 screw, screw hole depth > 3mm.
- DIN Rail Mounting: Standard 35mm DIN RAIL.

配线图 Wiring Diagram


T022




T022-K



T023



T023-K



T024



T024-K



分类

T 总线模块

T 端子台

Y 电气控制

X 连接电缆

D 照明

H 电气配件

P 开关电源

G 辅材配件

F 气动附件



T022专利号: 201230161014.3
T023专利号: 200930166663.0
T024专利号: 20093016667.8

有关符合EU指令的产品请参阅
附-35

询问胜蓝

0755-8886 0059

当日出货

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Pluggable Terminal Blocks](#) category:

Click to view products by [siron](#) manufacturer:

Other Similar products are found below :

[57.510.0053](#) [721-104/026-047](#) [721-204/026-045](#) [MC 1.5/ 6-ST-3.5 GY AU](#) [ET02015000J0G](#) [860505](#) [860516](#) [860810](#) [GBPACX-12](#)
[93.731.4953.0](#) [PVP03-3,50](#) [PVS02-5,00](#) [1-1986160-3](#) [1377680000](#) [1531000000](#) [1546228-5](#) [ELFP03110](#) [ELFP10210](#) [ELFT07250](#)
[ELVD12100](#) [ELVF09400](#) [ELXH071G0E](#) [1725220000](#) [1760336](#) [1855000000](#) [19346](#) [1946309](#) [1973592](#) [19892](#) [25.320.4053.1](#) [25.320.4553.9](#)
[25.320.4753.1](#) [25.320.5453.1](#) [25.340.0353.1](#) [25.340.1053.1](#) [25.345.3553.0M001](#) [25.640.3553.1](#) [SH02-5,08](#) [SH06-3,81](#) [SH08-5,08](#) [SH08-](#)
[5,08-K](#) [SH12-5,08](#) [SHS04-5,00](#) [30.303](#) [30.305](#) [30.306](#) [PHP09-5,08](#) [25.193.0453.0](#) [25.320.4653.1](#) [25.332.2453.1](#)