

三菱J3/ES/JE 系列伺服电缆线 X300

三菱J3/ES/JEシリーズ用サーボケーブル
Servo cable for Mitsubishi J3/ES/JE series



- 省空间
- 伺服线
- 耐油耐热
- 柔软
- 电箱配线

非在産品
Items in the library of non-

询问胜蓝
0755-8886 0059 当日出货


● 特点 Features

- * 电缆护套由低粘性高耐磨损材料制成;
- * 具有高抗弯曲强度及高柔韧性;
- * 耐油和冷却剂, 耐划痕;
- * 适用于一般布线场所及拖链。
- * ケーブルのカバーは低粘り高耐摩耗材料でつくられます;
- * 高い曲げ強度と高柔軟性;
- * 耐油和冷却剂、耐划痕、冷却剂と並に強い、耐きず;
- * 普通の配線場所およびロータチェーンに適用。
- * Cable oversheath is made of low tack and high wear-resistance material;
- * With high flexural strength and high flexibility;
- * With oil and refrigerant resistance function, easy to leave scratch;
- * Applicable to general wiring situation and towing transmission places.

▲ 注意事项 Note

- 请参照下表, 选择伺服马达的规格。
- 请不要随意更改线束内部部品。
- Please refer to the table below to choose the wiring harness of the servo motor.
- Please don't change the wiring harness internal component of will.

● 订货范例 Order



注意: 全长标准长度为1000mm, 如需增加长度以1000mm递增。
Notice: The shortest length is 1000mm, such as increased to increase to 1000mm for increasing unit.

注意: 以上为标准型号。如需使用拖链线材, 请在型号后加“T”, 详情请咨询相关销售人员。

Notice: The above is standard cable model. If you want to use chain wire, Please sign "T" after the model. Please contact sales for more details.

● 端口对应列表 Port corresponding list

型号 Model	对应功率 Corresponding power	驱动器 Drive	对应马达(W) Corresponding motor	原厂型号 Original model
X300-1 X300-1T	100~600W	J3, J4 E, JE	HF-MP HG-MR HF-KP HG-KR HF-KE HG-KN HF-KN (13/23/43)	MR-PWS1CBL0-A1-L
X300-1H X300-1HT	750W	J3, J4 E, JE	HF-MP HG-KE HF-KR HG-KN HF-KP HG-KR HF-MR (73)	MR-PWS1CBL0-A1-L
X300-2/2T	100~750W	J3, J4 E, JE	HF-MP HG-KN HF-KP HG-KR HF-KE HG-MR HF-KW HF-KN (13/23/43/73)	B-MR-J3ENCBL0-L
X300-3	600~1000W	J3, J4 E, JE	HF-MP HG-KN HF-SR (51/52/81/102) HG-SR (51/52/81/102) HF-SN (52/102) HF-SE2JWI-S100 HF-SE102JWI-10	插头: MR-PWCNS4
X300-4H	2000W	J3, J4 E, JE	HF-SP (152) HF-SN (152) HG-SR (152) HF-SE152JWI-S100	插头: MR-PWCNS5
X300-5	2000~3000W	J3, J4 E, JE	HF-SP1(21/201/202/352) HF-SN(202/302) HG-SR(121/201/202/301/352)	插头: MR-PWCNS5
X300-5H	5000W	J3, J4	HF-SP(502) HG-SR(502)	
X300-6	600~5000W	J3, J4 JE	HF-SP (51/52/81/102/121/152/201/202/352/502) HG-SR(51/52/81/102/121/152/202/201/301/352) HF-SN (52/102/152/202/302) HF-SN HG-KN HG-SN (52/102/152/202/302)	MR-J3ENSCBL0-L
X300-7	750~2000W	E	HF-SE0JWI-S100 (52/102/152/202) HG-JR701M(4) HG-JR37K1M(4) HG-JR45K1M4HG JR5K1M4HG-JR601(4) HG-JR37K1(4)	/
X300-8	600~5000W	J3, J4 E, JE	HF-SP (51/52/102/121/152/201/202/352/502) HF-SN (52/102/152/202) HG-SR HG-SN (51/52/81/102/121/152/201/202/301)	插头: MR-BKCNS1

● 外形图 Outline

型号 Model	功能 Functions	缆线规格 Cable specification	外形图 Dimensions	电路图 Wiring Diagram
X300-1 X300-1T	伺服动力线 Servo drive cable	AWG20		
X300-1H X300-1HT	伺服动力线 Servo drive cable	AWG18		
X300-2 X300-2T	伺服编码器线 Servo encoder cable	AWG24		
X300-3	伺服刹车线 Servo brake cable	AWG22		
X300-4	伺服动力线 Servo drive cable	AWG17		
X300-4H	伺服动力线 Servo drive cable	AWG13		
X300-5	伺服动力线 Servo drive cable	AWG13		
X300-5H	伺服动力线 Servo drive cable	AWG10		
X300-6	伺服编码器线 Servo encoder cable	AWG24		
X300-7	伺服编码器线 Servo encoder cable	AWG24		
X300-8	伺服刹车线 Servo brake cable	AWG17		

电缆线
Cable

伺服电机
电缆线系列
Servo Motor Cables Series

分类

T 总线模块

T 端子台

Y 电气控制

X 连接电缆

D 照明

H 电气配件

P 开关电源

G 辅材配件

F 气动附件

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [siron manufacturer](#):

Other Similar products are found below :

[X300-2-4000](#) [X300-2-1000](#) [X300-2-2000](#) [X300-2-5000](#) [X320-3-2000](#) [X320-3-5000](#) [X320-3H-1000](#) [X320-3H-3000](#) [X320-3H-4000](#) [X320-3-3000](#) [X320-3-4000](#) [X320-3H-2000](#) [X320-3-1000](#) [X320-3H-5000](#) [X300-2-3000](#) [X210-5-5000](#) [X210-1-5000](#) [X210-2-2000](#) [X210-2-1000](#) [X210-1D-3000](#) [X210-2D-4000](#) [X210-3S-1000](#) [X210-4S-1500](#) [X210-5-3000](#) [X211-1-1500](#) [X210-4D-1000](#) [X210-4S-1000](#) [X210-5-1000](#) [X210-5-1500](#) [X210-5-2000](#) [X210-5S-1500](#) [X210-5S-2000](#) [X211-2-1000](#) [X211-2-3000](#) [X211-2-5000](#) [X212-1-1000](#) [X212-1-1500](#) [X210-3-3000](#) [X210-4D-6000](#) [X210-4S-2000](#) [X211-1-2000](#) [X210-2-3000](#) [X210-3-2000](#) [X210-3S-1500](#) [X210-4-1000](#) [X210-4-2000](#) [X210-1-1000](#) [X210-1D-1000](#) [X210-3-1500](#) [X210-4-3000](#)