



FABBRICA CAVI - ANTENNE - ACCESSORI TV

HF 240 PE

HIGH PERFORMANCE BROADBAND LOW LOSS 50 OHM COAXIAL
COMMUNICATION CABLE DESIGNED FOR USE IN WIRELESS APPLICATIONS

Class CPR **F_{ca}**

CU PEG LAS CS PE
ø 1,40 mm ø 3,80 mm ø 3,90 mm ø 4,30 mm ø 6,10 mm



|| A || || B || || C || || D || || E || ||

MECHANICAL DATA

A	INNER CONDUCTOR	PLAIN COPPER	ø 1,40 mm
B	DIELECTRIC	GAS INJECTED SKIN-FOAM-SKIN POLYETHYLENE	ø 3,80 mm
C	SHIELD	ALL + PET + ALL ADHESIVE TAPE	h. 15 mm
		- COVERAGE	100%
D	BRAID	TINNED COPPER	128 x 0,10 mm
		- COVERAGE	77%
E	SHEATH	CARBON BLACK POLYETHYLENE	ø 6,10 ± 0,10 mm
	- COLOUR	BLACK - RAL 9004	
	- PRINTING	## METER ## HF 240 PE HIGH PERFORMANCE LOW LOSS CABLE 50 OHM	
		1,40 / 3,80 / 6,10 MADE IN ITALY CE 58 WEEK/YEAR	

MINIMUM BENDING RADIUS (mm)

- SINGLE ø EXTERNAL X 5
- REPEATED ø EXTERNAL X 10

TEMPERATURE RANGE -40 °C / +75 °C

CABLE WEIGHT (Kg/Km)

- COPPER 23,3
- PLASTIC 18,1
- TOTAL 43,2

ELECTRICAL PROPERTIES at 20°C

IMPEDANCE @ 200 MHz	50 ± 1,5 Ohm	RESISTANCE	
		- INNER CONDUCT.	11,5 Ohm/Km
CAPACITANCE	80 pF/m	- BRAID	16,2 Ohm/Km
VELOCITY RATIO	84%	TENSION	
		- SHEATH	6,5 kV
		SPARK TESTING	

ATTENUATIONS dB/100 m.

		dB	W
5	MHz	1,8	3536
10	MHz	2,5	2500
30	MHz	4,1	1443
50	MHz	5,2	1118
150	MHz	8,9	645
220	MHz	10,9	533

MAX. POWER RATING W

		dB	W
450	MHz	16,2	373
600	MHz	18,7	323
800	MHz	21,9	280
900	MHz	22,9	264
1000	MHz	24,5	250
1500	MHz	30,8	204

		dB	W
1800	MHz	34,1	186
2000	MHz	36,7	177
2500	MHz	40,9	158
3000	MHz	45,5	144
5200	MHz	63,4	110
5800	MHz	67,6	104

STRUCTURAL RETURN LOSS dB

30 ÷ 450	MHz	>32	2000 ÷ 3000	MHz	>23
450 ÷ 1000	MHz	>29	3000 ÷ 4000	MHz	>23
1000 ÷ 2000	MHz	>26	4000 ÷ 5800	MHz	>14

SCREENING EFFECTIVENESS dB

100 ÷ 900	MHz	>95
900 ÷ 2000	MHz	>85
2000 ÷ 3000	MHz	>75

The producer reserves himself to make modification on the item without any notice.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Coaxial Cables](#) category:

Click to view products by [Siva Cavi](#) manufacturer:

Other Similar products are found below :

[89880-003-1000](#) [7810SB-010-1000](#) [9116-010-U500](#) [1807A-B59-U1000](#) [2020K8421-9X-CS3417](#) [275604-000](#) [935240-000](#) [9659-010-1000](#)
[980704-001](#) [33312-010-500](#) [CZ1589-000](#) [5022W0809-0CS3263](#) [10610-4-4](#) [EF8108-000](#) [1673B TIN100](#) [672525-001](#) [735A1-008-1000](#)
[8212-010-U500](#) [8263 010U500](#) [TCC-75-2](#) [9248 010U1000](#) [1694A 0081000](#) [8241F J5C1000](#) [7805R 008100](#) [9271 0061000](#) [5339Q5 009U500](#)
[89207 010100](#) [1369R 004500](#) [7915R 0101000](#) [833101-000](#) [1152A-A8R-500](#) [9907-E4X-U1000](#) [3092A-X7E-500](#) [100066-0049](#) [5021K1011-](#)
[0 ECJ5048-L](#) [4505R 0071000](#) [T-RAD-400-FR](#) [2410329-4](#) [L01030B0021](#) [60.7500-23](#) [51305](#) [BU-4150031024](#) [0026010](#) [L01001C0003](#) [BU-](#)
[4150030024](#) [BU-4150032048](#) [SMBM-SMBM17410](#) [50942](#) [L01000B0001](#)