

Features

- 5032 size miniature and lightweight SMD crystal units with low profile of 1.2mm
- Frequency range from 8MHz to 64MHz
- 2 pads SMD glass crystal units
- Excellent heat resistance, high precision
- Application for PDA, GPS, Smart factory, AV equipment, PC, Server, and etc.
- Contain Pb in sealed glass exempted by RoHs directive






Standard Specification

Item /Type	6I (6I Series SMD Crystal Units)
Frequency Range	8~64 MHz
Frequency Tolerance (at 25°C)	±30ppm, or specify
Frequency stability Over Operating Temperature	±30ppm, or specify
Operating Temperature Range	-20~+70°C, or specify
Shunt Capacitance (C ₀)	5pF Max.
Drive Level	1~200μW Max. (100μW Typ.)
Load Capacitance	10pF, 16pF, 20pF, or specify
Aging (at 25°C)	±3ppm /year Max.
Storage Temperature Range	-40~+85°C
Packing Unit	1000pcs./Reel


Equivalent Series Resistance

Fundamental			
8~10 MHz	150Ω Max.	12~40 MHz	50Ω Max.
10~12 MHz	100Ω Max.	40~64 MHz	100Ω Max.

Dimensions [mm]



Top View Crystal Connection



Top View Suggested Layout

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Crystals](#) category:

Click to view products by [SJK](#) manufacturer:

Other Similar products are found below :

[CS325S24000000ABJT](#) [718-13.2-1](#) [MC405 32.0000K-R3:PURE SN](#) [FC-135R 32.7680KF-A3](#) [7A-40.000MAAE-T](#) [7B-27.000MBBK-T](#)
[FL2000085](#) [9B-15.360MBBK-B](#) [9C-7.680MBBK-T](#) [ASH7K-32.768KHZ](#) [AT-41.600MAGQ-T](#) [BTD1062E05A-513](#) [LFX TAL066198Cutt](#)
[9C-14.31818MBBK-T](#) [FA-238 50.0000MB30X-K3](#) [FC-12M 32.7680KA-AC3](#) [SSPT7F-9PF20-R](#) [FX325BS-38.88EEM1201](#)
[LFX TAL065253Cutt](#) [LFX TAL066431Cutt](#) [XT9S20ANA14M7456](#) [XT9SNLANA16M](#) [646G-24-2](#) [7A-24.576MBBK-T](#) [7B-30.000MBBK-T](#)
[WX26-32.768K-6PF](#) [9B-14.31818MBBK-B](#) [CD1AM](#) [7B-25.000MAAE-T](#) [7A-14.31818MBBK-T](#) [6504-202-1501](#) [6526-202-1501](#) [FA-118T](#)
[27.1200MB50P-K0](#) [FC-135R 32.7680KA-A3](#) [ABM12-104-37.400MHZT](#) [ABLS-10.000MHZ-D3W-T](#) [BTJ112E01E-513](#) [BTJ722K01C-7067](#)
[BTL-20-513](#) [TSX-3225 24.0000MF15X-AC](#) [TSX-3225 16.0000MF18X-AC](#) [BTJ120E02C](#) [BTL-12-513](#) [7A-10.000MBBK-T](#) [7A-](#)
[11.0592MBBK-T](#) [ABM12-103-24.000MHZT](#) [CS325S25000000ABJT](#) [ABM3B-25.000MHZ-B2-X-T](#) [FC-135 32.7680KA-A5](#) [FX0800015](#)