

Hot air tool

## HG 2620 E

Folding box

EAN 4007841008338



### Function description

The flagship. Hot air tool HG 2620 E. 2300 W, digital temperature adjustment by joystick from 50 – 700 °C. Airflow control from 150 – 500 l/min. Features LCD display and residual heat indicator. Brushless motor, integrated fine dust filter, suitable for use on construction sites.

### Technical specifications

Output	2300 W
Temperature	50 – 700 °C
Airflow rate	150 – 500 l/min
Air pressure	4000 Pa
Motor, type	Brushless
Function, life expectancy, motor	10000 h
Temperature setting	in 10°C steps by joystick
Temperature display	LCD display
Heating element	Ceramic heating element
Loc function	Yes
Residual heat indicator	Yes
Function, hanger	No
Replaceable heating element	Yes
Restart protection	Yes
Thermal cut-out	Yes
Cord length	3 m
Dimensions (L x W x H)	358 x 91 x 95 mm
Mains power supply	220 – 230 V , 50 / 60 Hz
Model	Folding box

# Data sheet



Hot air tool

## HG 2620 E

Folding box

EAN 4007841008338

### Technical specifications

PU1, net weight	1,160 kg
Manufacturer's Warranty	1 year
PU1, EAN	4007841008338

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Heat Guns & Nozzles](#) category:*

*Click to view products by [Steinel](#) manufacturer:*

Other Similar products are found below :

[AES-IR550-63-PC-BRD](#) [IR-1000-P-N-13-LAMP](#) [298392-000](#) [TG-24-RFL-LGE-BOOT](#) [841201-000](#) [H-P28](#) [16806](#) [N-SL28](#) [N-D4515](#) [H-TS40](#) [T0058736881N](#) [T0058768745N](#) [ED-7-004-TRANSFORMER-115V](#) [T0058736870N](#) [T0058736814N](#) [T0058727773N](#) [CV1981-ST-230V1600W-EU](#) [CV-1981-PID-S-BRSH42V120V](#) [T0058762858](#) [T0058727812](#) [4007841009595](#) [HG 2220 E](#) [HG 2320 LCD](#) [HL 1620 S](#) [HL 1920 E](#) [HL 2020 E](#) [1082](#) [T6964](#) [ML100](#) [T0058735938](#) [AD-1261-9](#) [34412](#) [T0058735937](#) [34001](#) [34422](#) [34036](#) [T0058727821](#) [34008](#) [34024](#) [HCT-HTR120](#) [34042](#) [34002](#) [34424](#) [34022](#) [34020](#) [34006](#) [34018](#) [34040](#) [34016](#) [34438](#)