

8 7 6 5 4 3 2 1

YHLZR-__						
CATALOG NUMBER	INTERNAL RESISTOR	COLOR		MARKING		
		SIDE A	SIDE B	FRONT/REAR	SIDE A	SIDE B
YHLZR-1	RLR20C2702GR 27K ±2% 1/2W	BLUE	NATURAL	—	27K Ω	—
YHLZR-2	RLR20C4301GR 4.3K ±2% 1/2W	BLUE	BLACK	—	4.3K Ω	—
YHLZR-3	RLR20C5801GR 5.8K ±2% 1/2W	BLACK	BLACK	—	5.8K Ω	—
YHLZR-4	RLR20C6201GR 6.2K ±2% 1/2W	YELLOW	YELLOW	—	6.2K Ω	—
YHLZR-5	RLR20C9101GR 9.1K ±2% 1/2W	BLACK	ORANGE	—	9.1K Ω	—
YHLZR-6	RLR07C10R0GR .01K ±2% 1/4W	YELLOW	BLACK	—	.01K Ω	—
YHLZR-7	RLR07C1200GS .12K ±5% 1/4W	YELLOW	GREEN	—	.12K Ω	—
YHLZR-8	RNC60K5112FR 51.1K ±1% 1/4W	YELLOW	BLUE	—	51.1K Ω	—
YHLZR-9	RLR20C1202GR 12K ±2% 1/2W 0% FAILURE AT 50% RATED W/1000 HOURS	YELLOW	RED	—	12K Ω	—
YHLZR-10	RLR07C102FS 1K ±1% 1/4W 001% FAILURE AT 50% RATED W/1000 HOURS	YELLOW	NATURAL	—	1K Ω	—
YHLZR-11	RLR20C2402GR 24K ±2% 1/2W	BROWN	BROWN	—	24K Ω	—
YHLZR-13	RLR07C2400GR .24K ±2% 1/4W	BROWN	BROWN	—	.24K Ω	—
YHLZR-14A	RLR20C1001GR 1K ±2% 1/2W	GREEN	GREEN	—	1K Ω	—
YHLZR-15A	RLR20C2701GR 2.7K ±2% 1/2W	BLACK	RED	—	2.7K Ω	—
YHLZR-16	RLR20C71R5FR .0715K ±1% 1/2W	RED	ORANGE	—	.0715K Ω	—
YHLZR-17	RWR80S2001FR 2.0K ±1% 2W	GREEN	BROWN	—	2K Ω	—
YHLZR-18	RLR20C4301GR 4.3K ±2% 1/2W	BROWN	BROWN	—	4.3K Ω	—
YHLZR-19	RLR20C2700FR .27K ±1% 1/2W	BROWN	BROWN	—	.27K Ω	—
YHLZR-20	RLR20C8200FR .82K ±1% 1/2W	BROWN	BROWN	—	.82K Ω	—
YHLZR-21	RLR07C2322FR 23.2K ±1% 1/4W	BROWN	BROWN	—	23.2K Ω	—
YHLZR-22	RLR07C2151FR 2.15K ±1% 1/4W	BROWN	BROWN	—	2.15K Ω	—
YHLZR-23	RLR07C1691FR 1.69K ±1% 1/4W	BROWN	BROWN	—	1.69K Ω	—
YHLZR-24	RLR07C7500FR .75K ±1% 1/4W	BROWN	BROWN	—	.75K Ω	—
YHLZR-25	RLR07C4870FS .487K ±1% 1/4W	BROWN	BROWN	—	.487K Ω	—
YHLZR-26	RLR07C3160FR .316K ±1% 1/4W	BROWN	BROWN	—	.316K Ω	—
YHLZR-27	RLR07C2320FR .232K ±1% 1/4W	BROWN	BROWN	—	.232K Ω	—
YHLZR-28	RNC55H1601DR 1.6K ±0.5% 1/10W	BROWN	BROWN	—	1.6K Ω	—
YHLZR-29	RLR07C1501FR 1.5K ±1% 1/4W	BROWN	BROWN	—	1.5K Ω	—
YHLZR-30	RNC60H3001DR 3K ±0.5% 1/4W	BROWN	BROWN	—	3K Ω	—
YHLZR-31	RLR07C1602GR 16K ±2% 1/4W	BROWN	BROWN	—	16K Ω	—
YHLZR-32	RNC55H1003FR 100K ±1% 1/10W	BROWN	BROWN	—	100K Ω	—
YHLZR-33	RLR07C1002GR 10K ±2% 1/4W	BROWN	BROWN	—	10K Ω	—
YHLZR-34	RNC55J1203BS 120K ±1% 1/10W	BROWN	BROWN	—	120K Ω	—
YHLZR-35	RNC60H8062BS 80.6K ±1% 1/4W	BROWN	BROWN	—	80.6K Ω	—
YHLZR-36	RLR07C3302JR 33K ±5% 1/4W	BROWN	BROWN	—	33K Ω	—
YHLZR-37	RWR80N15R0FS .015K ±1% 2W	BROWN	BROWN	—	.015K Ω	—
YHLZR-38	RLR07C4991FS 4.99K ±1% 1/4W	BROWN	BROWN	—	4.99K Ω	—
YHLZR-39	RLR20C3320FR .332K ±1% 1/2W	BROWN	BROWN	—	.332K Ω	—

YHLZR-__ (CONT'D)						
CATALOG NUMBER	INTERNAL RESISTOR	COLOR		MARKING		
		SIDE A	SIDE B	FRONT/REAR	SIDE A	SIDE B
YHLZR-40	RLR20C3650FR .365K ±1% 1/2W	BROWN	BROWN	—	.365K Ω	—
YHLZR-41	RLR07C2003FR 200K ±1% 1/4W	BROWN	BROWN	—	200K Ω	—
YHLZR-42	RLR20C1000FS 100K ±1% 1/2W	BROWN	BROWN	—	100K Ω	—
YHLZR-43	RLR07C4702GR 47K ±2% 1/4W	BROWN	BROWN	—	47K Ω	—
YHLZR-44	RNC60H2003FS 200K ±1% 1/4W	BROWN	BROWN	—	200K Ω	—
YHLZR-45	RWR81S1500GR .15K ±2% 1W	BROWN	BROWN	—	.15K Ω	—
YHLZR-48	RWR80S1001FR 10K ±1% 2W	BROWN	BROWN	—	1K Ω	—
YHLZR-49	RNC60J2212FM 22.1K ±1% 1/4W	BROWN	BROWN	—	22.1K Ω	—
YHLZR-50	RLR07C1240FM 0.124K ±1% 1/4W	BROWN	BROWN	—	0.124K Ω	—
YHLZR-51	RN60D4120F 0.412K ±1% 1/4W	BROWN	BROWN	—	0.412K Ω	—

YHLZD-__								
CATALOG NUMBER	SEMI-CONDUCTOR (DIODE)	INTERNAL RESISTOR	COLOR		MARKING			
			SIDE A	SIDE B	FRONT/REAR	SIDE A	SIDE B	
YHLZD-1	JAN IN3613	RLR32C1500GR .15K ±2% 1W	BLUE	ORANGE	—	+	-	
YHLZD-2	JAN IN5126 OR LS10318-2	RLR32C1500GR .15K ±2% 1W	RED	RED	—	—	—	
YHLZD-3	JAN IN6130 OR LS10318-3	RLR32C1500GR .15K ±2% 1W	GREEN	GREEN	—	—	—	
YHLZD-8	JAN IN3613	—	BLACK	WHITE (NATURAL)	—	+	-	
YHLZD-9	JAN IN3613	—	RED	RED	—	A	C	
YHLZD-11	JAN IN3022	—	RED	GREEN	—	A	C	
YHLZD-14	R4615	—	RED	BLUE	—	A	C	
YHLZD-15	3SM6 OR IN 5552	—	RED	NATURAL	—	A	C	
YHLZD-23	UZ1325	—	GREEN	BLUE	—	A	C	
YHLZD-24	UD2860	—	GREEN	ORANGE	—	A	C	
YHLZD-26	IN5061	—	GREEN	BLACK	—	A	C	
YHLZD-28	JANTX IN4965	—	BROWN	BLACK	—	A	C	
YHLZD-29	JANTX IN5551	—	BROWN	YELLOW	—	A	C	
YHLZD-30	JANTX IN5618	—	BROWN	ORANGE	—	A	C	
YHLZD-31	JANTX IN4971	—	GREEN	YELLOW	—	A	C	
YHLZD-32	JANTX IN3613	—	BLUE	YELLOW	—	A	C	
YHLZD-33	JANTX IN5552	—	RED	YELLOW	—	A	C	
YHLZD-34	JANTX IN5553	—	RED	BROWN	—	A	C	
YHLZD-35	JANTX IN4148-1	—	RED	BLACK	—	A	C	
YHLZD-38	JANTX IN4972	—	BLUE	BLUE	—	A	C	
YHLZD-39	JANTX IN5467	—	NATURAL	RED	—	A	C	
YHLZD-40	JANTX IN6122	—	NATURAL	GREEN	—	A	C	
YHLZD-41	JANTX IN6158	—	NATURAL	BLUE	—	A	C	

NOTES: SEE SHEET 1.

THIS DRAWING IS UNLESS OTHERWISE SPECIFIED TO BE IN ACCORDANCE WITH THE CUSTOMER'S DRAWING. THE CUSTOMER'S DRAWING SHALL BE CONSULTED FOR THE LATEST REVISION.

BE	REVISED PER ECN6186	SDH	SDH	01-08-04
BD	REVISED PER ECN7740	JRD	SDH	01-08-03
BC	REVISED PER ECN7384	JRD	SDH	07-11-02
BB	REVISED PER ECN5597	JRD	SDH	01-22-02
BA	REVISED PRINT PER ECN5302	JRD	SDH	10-03-01
52	REVISED PRINT PER ECN4848	JRD	SDH	06-29-01
REV	REVISION DESCRIPTION	BY	CHKD	DATE

TERMINAL BLOCK MODULE ASSEMBLY
 CAT NO: YHLZ-__ (SEE TABLE)
 GRADE NO: 69922
 SIZE: 0

SOURIAU
 Connection Technology

CUSTOMER
 www.focconnect.com

APPROVAL: DRAWN: DET 12-08-02
 DESGN: ESK 12-10-02
 INFO: HS 12-10-02
 DR: NXX 12-10-02
 DRAWING NO: N/A
 REV: N/A
 SHEET 2 OF 2
 ME10

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminal Junction Modules](#) category:

Click to view products by [Sunbank](#) manufacturer:

Other Similar products are found below :

[00175510302](#) [00175520502](#) [00175530502](#) [00175510202](#) [00175510402](#) [00175520202](#) [00175520402](#) [00175520602](#) [591900-1](#) [CTJ116E01D-513](#) [CTJ-2A-01](#) [CTJ-3A-04](#) [CTJ720E01B](#) [M81714/60-20-06](#) [M81714/60-20-2](#) [M81714/60-22-01](#) [RBTB16-3W](#) [CTE220-10-102-1050](#) [CTJ-3A-03-4021](#) [CTJ-3A-06-4021](#) [CTJ-3D-10](#) [CTJ620E06N-513](#) [TJ11E-06-04](#) [TJM112701](#) [TJM116701](#) [TJM116702](#) [TJS316702](#) [YCTD160E01FC108000](#) [YHLZ-22](#) [YHLZR-45](#) [TJM120702](#) [TJM120704](#) [TJS316701](#) [YHLZE8-8](#) [YHLZ16-8](#) [YHLZ16-4](#) [YHLZ16-2](#) [CTJ716K01D](#) [TJM120601](#) [TJM120605](#) [YCTJ420E021C098000](#) [CTD126E01A](#) [CTJ120E02C-6148](#) [CTJ120E02C-6162](#) [CTJ716E01D-6181](#) [M81714/65-20-2](#) [YHLZ-8](#) [BTJ122E05E-513](#) [BTJ120E04A-513](#) [SJM020401](#)