



■ 25x25x10



Model	Bearing ● VAPO	Rating Voltage (VDC)	Power Current (mA)	Power Consumption (WATTS)	Speed (RPM)	Air Flow (CFM)	Static Pressure (Inch-H ₂ O)	Noise (dBA)	Weight (g)
MC25100V1-0000-A99	●	5	120	0.60	13000	3.5	0.25	23.0	7.5
MC25100V2-0000-A99	●	5	85	0.43	10000	3.0	0.18	16.0	7.5

■ 30x30x10



Model	Bearing ● VAPO	(VDC)	(mA)	(WATTS)	(RPM)	(CFM)	(Inch-H ₂ O)	(dBA)	(g)
MC30100V1-0000-A99	●	5	120	0.60	9500	5.5	0.15	23.0	8.6
MC30100V2-0000-A99	●	5	75	0.38	8000	4.6	0.12	20.0	8.6

■ 35x35x10



Model	Bearing ● VAPO	(VDC)	(mA)	(WATTS)	(RPM)	(CFM)	(Inch-H ₂ O)	(dBA)	(g)
MC35100V1-0000-A99	●	5	150	0.75	9500	7.0	0.18	28.0	10.5
MC35100V2-0000-A99	●	5	75	0.38	7500	6.5	0.12	22.0	10.5

■ 40x40x10



Model	Bearing ● VAPO	(VDC)	(mA)	(WATTS)	(RPM)	(CFM)	(Inch-H ₂ O)	(dBA)	(g)
MB40100V2-0000-A99	●	5	180	0.90	5800	7.0	0.11	27.0	17.0
ME40101VX-0000-A99	●	12	130	1.60	8500	9.9	0.24	36.1	15.0
ME40101V1-0000-A99	●	12	90	1.08	7000	8.0	0.19	32.0	13.5
MB40101V2-0000-A99	●	12	80	0.96	5800	7.0	0.11	27.0	17.0



Model	Bearing ○ Sleeve	(VDC)	(mA)	(WATTS)	(RPM)	(CFM)	(Inch-H ₂ O)	(dBA)	(g)
EB40100S2-0000-999	○	5	205	1.03	5800	7.0	0.11	27.0	17.0
EB40101S2-0000-999	○	12	90	1.08	5800	7.0	0.11	27.0	17.0

■ 50x50x10



Model	Bearing ● VAPO	(VDC)	(mA)	(WATTS)	(RPM)	(CFM)	(Inch-H ₂ O)	(dBA)	(g)
MB50100V2-0000-A99	●	5	235	1.18	4300	11.0	0.11	26.0	21
MB50101V2-0000-A99	●	12	105	1.26	4300	11.0	0.11	26.0	20



Model	Bearing ○ Sleeve	(VDC)	(mA)	(WATTS)	(RPM)	(CFM)	(Inch-H ₂ O)	(dBA)	(g)
EB50100S2-0000-999	○	5	245	1.23	4300	11.0	0.11	26.0	21
EB50101S2-0000-999	○	12	120	1.44	4300	11.0	0.11	26.0	20

* If you need special specification. Please contact Sunon sales.

* Specifications are subject to change without notice. Specifications in this catalog are for reference. More Sunon products information please visit SUNON web site at <http://www.sunon.com>.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [sunon](#) manufacturer:

Other Similar products are found below :

[MB50151V2-000U-A99](#) [3113HQ/MC40101V2-Q00U-S99](#) [UF3A3-700](#) [UB3H3-500](#) [PMB2475PNB3-AY.\(2\).GN](#) [KD1208PHB1.13.\(2\).GN](#)
[KD1204PKB3 \(2\).GN](#) [GB1205PKV2-8AY.F.GN](#) [EE60251B1-000U-C99](#) [3236HQ/PF40281B1-D17U-S99](#) [A2175HBT-TC.R.GN](#) [B2-10](#)
[SM203-13002](#) [PE80254V1-000U-A99](#) [PF92251V1-1000U-A99](#) [ME80201V2-000U-A99](#) [PE92252B1-000C-AB9](#) [MC30101V2-000C-](#)
[A99\(165mm\)](#) [MF20100V4-1Q04C-G99](#) [PE92254B2-000C-F99](#) [MC30150V1-000C-A99](#) [PE80252B1-000C-AB9](#) [MF20060V3-1Q07A-G99](#)
[MC25100V2-000C-G99](#) [PMD2412PMB1-A\(2\).R.GN.I55](#) [AB1123-HST.GN](#) [PF80381BX-000U-A99](#) [MF25100V1-1000U-A99](#) [PF80251V1-](#)
[1000U-F99](#) [PF92381B1-000U-A99](#) [VF40281BX-000U-A9H](#) [40HVH120M](#) [LA004-024A83DY](#) [SM203-14001Y](#) [MF80251V1-1000U-G99](#)
[EE60251B2-000U-999](#) [SM203-13004Y](#) [SM205-13001](#) [F92-B](#) [FG-8/45](#) [MEC0382V2-000U-A99](#) [LA004-011A99DN](#) [SF11592A-](#)
[1092HSL.GN](#) [CF4113HBL-000U-ABD](#) [SF23092A-2092MBL.GN](#) [MF20100V1-1000U-A99](#) [DP203A-2123LBL.\(5\).GN](#) [PF40281B3-000U-](#)
[A99](#) [LM310-001A99DN](#) [KD2406PKB2.\(2\).GN](#)