



- NOTES:**
1. INSERTION LOSS: 0.25 dB MAX.
  2. OPERATION TEMP: -40°C TO +80°C.
  3. MATERIALS:  
 ST2 ADAPTER:  
 BODY - ZINC ALLOY  
 RETENTION WASHER - BRASS, NICKEL PLATED  
 SLEEVE - CERAMIC, SINGLE-MODE  
 - COPPER ALLOY, MULTI-MODE  
 DUST CAPS - PVC  
 NUT - COPPER ALLOY, NICKEL PLATED  
 LOCKWASHER - STEEL, NICKEL PLATED  
 FLANGE - ZINC ALLOY
  4. THIS PRODUCT IS RoHS COMPLIANT.

PART NUMBER	ST2 ADAPTER SEE NOTE 3	DUST CAP COLOR	FLANGE FINISH
EHST2	SINGLE-MODE	RED	NICKEL
EHST2M	DOUBLE-MODE	BLACK	NICKEL
EHST2B	SINGLE-MODE	RED	BLACK CHROME
EHST2MB	DOUBLE MODE	BLACK	BLACK CHROME

**CUSTOMER DRAWING**

					THIS DRAWING DESCRIBES A DESIGN CONSIDERED PROPRIETARY IN NATURE, DEVELOPED AND MANUFACTURED BY SWITCHCRAFT INC. AND IS RELEASED ON A CONFIDENTIAL BASIS FOR IDENTIFICATION PURPOSES ONLY.				
					SIZE	WIDTH	MULT	LBS/M	TEMPER
					FINISH			MATERIAL	
					SPEC No.			SPEC No.	
					FIRST USED ON		SCALE 1.5:1		
B	27621	12-4-15	TO	TJK	DATE DRAWN	BY	CHKD	APVD	<b>Switchcraft®</b>
A	26306	12/1/08	RS	TJK	5/12/08	JGK	RS	TJK	
					SHEET 1 OF 1				
REV	ECO NUMBER	DATE	BY	APVD	NAME			PART No.	REV
REVISIONS					E SERIES ST2 FIBER OPTIC ADAPTER, RoHS			EHST2_SERIES	B

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Fibre Optic Connectors](#) category:*

*Click to view products by [Switchcraft](#) manufacturer:*

Other Similar products are found below :

[0004700001](#) [6100-R](#) [6313](#) [F709034706](#) [F709722200](#) [F709730000](#) [F718183204](#) [F727403500](#) [F727752800](#) [8119](#) [9440F20-27S-190](#) [944-120-6001](#) [9441F10SL-3S](#) [9444W28-21S](#) [9444W36-10S](#) [9446F10SL-4S](#) [9446W20-16S](#) [953-101-5310-P](#) [954-101-57202B](#) [A0270169](#) [12-9122](#) [12-5702](#) [AX101713](#) [AX102420](#) [AX103923](#) [AX104024](#) [AX104193](#) [AX104230](#) [AX104562](#) [AX105203-B25](#) [AX105205-S1](#) [EHSC2M](#) [17-300800](#) [181-011-126](#) [181-011-S](#) [181-057-126](#) [HRFC-R2\(40\)](#) [NKSOPBUY](#) [20500002116](#) [2064996-1](#) [20800001065](#) [2170](#) [9132](#) [2612](#) [2620](#) [9291](#) [9440F16-10S](#) [9440F20-18S](#) [9446F16-10S-190](#) [953-106-50231](#)