

MILAN S.r.l. a socio unico

Head Office – Export department:  
 Viale Europa, 74  
 20090 Cusago (MI) Italy  
 T. +39 02 9039.4556-4158  
 F. +39 02 9039.4551  
 www.taskercables.com

Ufficio Commerciale e Centro Distribuzione  
 Viale Europa 72 Strada F12  
 20090 Cusago (MI) Italy  
 T. +39 02 9039.0037-0059  
 F. +39 02 9039.0049  
 www.tasker.it

## Technical Datasheet

**Halogen Free**

**tasker® T42 PUR – 7x0.40/4.80/7.10**

**FirestoP®**

### 12G-SDI Coaxial Video Cable 75 Ω - Outdoor Use



**CATEGORY** Coaxial cable 75 Ω (See Video Catalogue)

**APPLICATIONS** Digital video for broadcast and high definition video installation

- A:** Extra Flex Polyurethane **PUR** Sheath. Available in different colors. Flame Retardant, Halogen Free, UV, water, chemical and oil resistant. Cable suitable for Drag Chain and Outdoor installations. Outer Diam. Ø 7,10 (±0,10) mm.
- B:** First Shielding O.F.C. tinned copper Braid covering 89%
- C:** Second Shielding O.F.C. tinned copper Braid covering 86%.
- D:** Core Insulation with Gas Inject Foam PE. Diam. Ø 4,80 (±0,10) mm.
- E:** O.F.C. Red Copper stranded formation 7x0,40 mm. Nom. Cross section 1x0,88 mm<sup>2</sup>.

**MARKING** **tasker® T42 PUR – 1x0,88 mm<sup>2</sup> (75Ω) – O.F.C. - GAS INJECTED FHDPE – EXTRA-FLEX PUR SHEATH COAX VIDEO HDTV/SDI CABLE - FirestoP® - Halogen Free - Made in Italy**

**CUSTOM PRODUCTION** This product may be custom produced also in **L.S.Z.H.** polymer, **PE, PVC**, with or without Metallic Armor.

#### Cable Properties

<b>Conductor Resistance</b>	21 Ω/Km
<b>Capacity Core/Shield</b>	53,0 pF/m
<b>Velocity of Propagation</b>	86%
<b>Impedance</b>	75 Ω
<b>Nom. Delay</b>	4,1 ns/m
<b>HD-SDI Max Distance</b>	100 m
<b>Operative Temperature</b>	-40/+80°C

MILAN S.r.l. a socio unico

**Head Office – Export department:**  
 Viale Europa, 74  
 20090 Cusago (MI) Italy  
 T. +39 02 9039.4556-4158  
 F. +39 02 9039.4551  
 www.taskercables.com

**Ufficio Commerciale e Centro Distribuzione**  
 Viale Europa 72 Strada F12  
 20090 Cusago (MI) Italy  
 T. +39 02 9039.0037-0059  
 F. +39 02 9039.0049  
 www.tasker.it

**Attenuation dB/100 m.**

<b>10 MHz</b>	2,03
<b>100 MHz</b>	6,71
<b>1000 MHz</b>	22,5
<b>2000 MHz</b>	33,98
<b>3000 MHz</b>	44,96
<b>4500 MHz</b>	52,79
<b>6000 MHz</b>	70,01

**recommended installation distances**

<b>HD-SDI</b>	120
<b>3G-SDI</b>	100
<b>6G-SDI</b>	70
<b>12G-SDI</b>	70

**Drag Chain Test**

<b>Min. bending Radius Moved</b>	14 x O.D.
<b>Max Number of Cycle</b>	500000
<b>Max Speed</b>	3,3 m/s
<b>Max Accellation</b>	4,0 m/s <sup>2</sup>

<b>USE</b>	<b>X</b>	Indoor	Interno Edificio	<b>INSTALLATION</b>	<b>X</b>	Fixed	Fissa	<b>INFORMATION</b>	<b>X</b>	RoHS3 Compliant
<b>Impiego</b>	<b>X</b>	Outdoor Limited	Esterno Limitato	<b>Posa</b>	<b>X</b>	Restricted Mobile	Mobile Limitata	<b>Informazioni</b>	<b>X</b>	Ver. C / 07.01.19
	<b>X</b>	Outdoor	Esterno		<b>X</b>	Mobile	Mobile			
		Outdoor Direct Burial	Esterno Interrato		<b>X</b>	Mobile in Drag Chain	Mobile in Catena			

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Coaxial Cables](#) category:*

*Click to view products by [Tasker](#) manufacturer:*

Other Similar products are found below :

[89880-003-1000](#) [CY2389-000](#) [8221-010-U1000](#) [9116-010-U500](#) [1322R-010-1000](#) [1807A-B59-U1000](#) [2020K8421-9X-CS3417](#) [9251-010-1000](#) [9275-010-U1000](#) [935240-000](#) [980704-001](#) [CF2823-000](#) [33312-010-500](#) [CZ1589-000](#) [5022W0809-0CS3263](#) [10610-4-4](#) [EF8108-000](#) [672525-001](#) [144517-000](#) [735A1-008-1000](#) [8212-010-U500](#) [480414-000](#) [7915A 009U1000](#) [5024A1311-0](#) [1281S5 010250](#) [1530A 010U1000](#) [9248 010U1000](#) [9244 0101000](#) [1694A 0081000](#) [1190A 0101000](#) [8241F J5C1000](#) [1674A TIN50](#) [7915A 0091000](#) [9066 0031000](#) [7805R 008100](#) [1674A TIN100](#) [9116SB 0101000](#) [1613A 0101000](#) [1807A B591000](#) [5339Q5 009U500](#) [539945 0091000](#) [9116R 0101000](#) [89207 010100](#) [9058 0101000](#) [8241A 0101000](#) [DA7805R 0101000](#) [C6424](#) [1369R 004500](#) [7915R 0101000](#) [7809WB 0101000](#)