



RECOMMENDED HOLE LAYOUT

- 1 THE NOTED DIMENSIONS APPLY AT THE INTERSECTION OF THE POST AND THE HOUSING.
- 2 FOR ACTIVE POSITION SIZES 4 AND ABOVE, POSTS WILL BE SELECTIVELY SWAGED TO PROVIDE CONNECTOR RETENTION TO THE PC BOARD UNTIL SOLDERED. FOR POSITION SIZE 2, POSTS WILL BE KINKED.(SEE TABLE FOR RETENTION FEATURE LOCATION).
- 3 BREAKAWAY NOTCH ANGLE CAN BE ORIENTED TO THE RIGHT (AS SHOWN) OR TO THE LEFT.
- 4 .000100-.000200 MATTE TIN-LEAD OVER .000050 NICKEL, ON ENTIRE POST.
- 5 .000100-.000200 BRIGHT TIN OVER .000050 NICKEL, ON ENTIRE POST.
- 6 .000100-.000200 MATTE TIN OVER .000050 NICKEL, ON ENTIRE POST.
- 7 HIGH TEMPERATURE CONFIGURATION.
- 8 OBSOLETE PARTS: OBSOLETE CIS STREAMLINING PER D.RENAUD/D.SINISI.

OBSOLETE	6	1,2,39,40	1,2,39,40	3.984	3.900	39	80	7-104355-0
	6	1,2,29,30	1,2,29,30	2.984	2.900	29	60	6-104355-9
	6	1,2,24,25	1,2,24,25	2.484	2.400	24	50	6-104355-8
	6	1,2,19,20	1,2,19,20	1.984	1.900	19	40	6-104355-7
	6	1,2,16,17	1,2,16,17	1.684	1.600	16	34	6-104355-6
	6	1,2,14,15	1,2,14,15	1.484	1.400	14	30	6-104355-5
	6	1,2,13,14	1,2,13,14	1.384	1.300	13	28	6-104355-4
	6	1,2,12,13	1,2,12,13	1.284	1.200	12	26	6-104355-3
	6	1,2,11,12	1,2,11,12	1.184	1.100	11	24	6-104355-2
	6	1,2,10,11	1,2,10,11	1.084	1.000	10	22	6-104355-1
	6	1,2,9,10	1,2,9,10	.984	.900	9	20	6-104355-0
	6	1,2,8,9	1,2,8,9	.884	.800	8	18	5-104355-9
	6	1,2,7,8	1,2,7,8	.784	.700	7	16	5-104355-8
	6	1,2,6,7	1,2,6,7	.684	.600	6	14	5-104355-7
	6	1,2,5,6	1,2,5,6	.584	.500	5	12	5-104355-6
OBSOLETE	6	1,2,4,5	1,2,4,5	.484	.400	4	10	5-104355-5
	6	1,2,3,4	1,2,3,4	.384	.300	3	8	5-104355-4
	6	1,2,3	1,2,3	.284	.200	2	6	5-104355-3
OBSOLETE	6	1,2,39,40	1,2,39,40	3.984	3.900	39	80	2-104355-0
	6	1,2,29,30	1,2,29,30	2.984	2.900	29	60	1-104355-9
	6	1,2,24,25	1,2,24,25	2.484	2.400	24	50	1-104355-8
	6	1,2,19,20	1,2,19,20	1.984	1.900	19	40	1-104355-7
	6	1,2,16,17	1,2,16,17	1.684	1.600	16	34	1-104355-6
	6	1,2,14,15	1,2,14,15	1.484	1.400	14	30	1-104355-5
	6	1,2,13,14	1,2,13,14	1.384	1.300	13	28	1-104355-4
	6	1,2,12,13	1,2,12,13	1.284	1.200	12	26	1-104355-3
	6	1,2,11,12	1,2,11,12	1.184	1.100	11	24	1-104355-2
	6	1,2,10,11	1,2,10,11	1.084	1.000	10	22	1-104355-1
	6	1,2,9,10	1,2,9,10	.984	.900	9	20	1-104355-0
	6	1,2,8,9	1,2,8,9	.884	.800	8	18	104355-9
	6	1,2,7,8	1,2,7,8	.784	.700	7	16	104355-8
	6	1,2,6,7	1,2,6,7	.684	.600	6	14	104355-7
	6	1,2,5,6	1,2,5,6	.584	.500	5	12	104355-6
OBSOLETE	6	1,2,4,5	1,2,4,5	.484	.400	4	10	104355-5
	6	1,2,3,4	1,2,3,4	.384	.300	3	8	104355-4
	6	1,2,3	1,2,3	.284	.200	2	6	104355-3
	6	1,2	1,2	.184	.100	1	4	104355-2
OBSOLETE	6	1	1	.084	-	-	2	104355-1
	6	1	1	.084	-	-	2	104355-1

REMARKS	PLATING	ROW N	ROW M	C	B	A	NO OF POSN	ASSEMBLY PART NUMBER
HOLD-DOWN POST CONFIG LOCATION								

THIS DRAWING IS A CONTROLLED DOCUMENT.

DIMENSIONS: INCHES	TOLERANCES UNLESS OTHERWISE SPECIFIED:	DIN M. PASTAL 04FEB88	APVD R. FEIDT 09FEB88	NAME
0 PLC ± -	1 PLC ± -	2 PLC ± -	3 PLC ± .005	4 PLC ± -
ANGLES ± -				
MATERIAL HOUSING POST: COPPER ALLOY	FINISH SEE TABLE	WEIGHT -	SIZE A1	CAGE CODE 00779
CUSTOMER DRAWING		SCALE 4:1	SHEET 1 OF 1	REV

STE TE Connectivity
 HEADER ASSEMBLY, MOD II, BREAKAWAY, RIGHT ANGLE, DOUBLE ROW, .100X.100

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [TE Connectivity](#) manufacturer:

Other Similar products are found below :

[892-18-020-10-001101](#) [58102-G61-06LF](#) [582553-1](#) [0009485154](#) [009176003701906](#) [0050291907](#) [LY20-4P-DT1-P1E-BR](#) [02.125.8002.8](#)
[609-3404](#) [61062-3](#) [61082-181009](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [641991-4](#) [644827-2](#) [65817-](#)
[010LF](#) [65817-015LF](#) [65863-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68645-018](#) [68648-049](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-](#)
[4853B](#) [707-5020](#) [707-5028](#) [71.350.2428.0](#) [71918-208LF](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [787-8014-00](#) [79531-3000](#)
[FCN-360C032-B](#) [FCN-367T-T012/H](#) [FCN-723D010/2](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#)