

REV.	DESIGN	MATERIAL	SURFACE	WIRE RANGE	INSULATION	STRIP FORM	A	B	C	D	E	CRIMP DATA		
REV.	Ausführung	Werkstoff	Oberfläche	Drahtgrößen Bereich [mm²]	Isolations [mm]	WIRE CRIMP Drahtcrimp Bandware	INSUL.-CRIMP Insul.-Crimp Bandware	CRIMP DIMENSION (mm) Crimpabmessungen (mm)					AND CRIMP TOOL Crimpdaten u. Crimpwerkzeuge	
A17	2367105-6	A	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.35-0.5 FLR	1.1-1.4	E = 2.4 G = 2.3 D <sub>Dr</sub> = 1.0	H = 2.9 K = 2.9 D = 1.4	2.5	3.8	5.7	18.8	0.2
A17	2367105-3	A	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.35-0.5 FLR	1.1-1.4	E = 2.4 G = 2.3 D <sub>Dr</sub> = 1.0	H = 2.9 K = 2.9 D = 1.4	2.5	3.8	5.7	18.8	0.2
A17	2367105-1	A	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.35-0.5 FLR	1.1-1.4	E = 2.4 G = 2.3 D <sub>Dr</sub> = 1.0	H = 2.9 K = 2.9 D = 1.4	2.5	3.8	5.7	18.8	0.2
A17	965901-1	A	1	CuSn4	PRETINNED vorverzinkt min. 0.8µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3	4	5.5	18.8	0.4
A17	965899-1	A	1	CuSn4	PRETINNED vorverzinkt min. 0.8µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3	4	5.5	18.8	0.4
A17	928876-1	A	1	CuSn4	PLAIN BLANK	0.5-1.0 FLK	2.0-2.7	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.9 K = 4.1 D = 2.4	3	4	5.5	18.8	0.4
A17	927775-7	M	1	CuNi12Zn24	PRETINNED vorverzinkt min. 0.8µm	0.5-1.0 FLK	2.0-2.7	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.9 K = 4.1 D = 2.4	3	4	5.5	18.8	0.4
A17	927775-6	M	1	CuSn4	PRETINNED vorverzinkt min. 0.8µm	0.5-1.0 FLK	2.0-2.7	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.9 K = 4.1 D = 2.4	3	4	5.5	18.8	0.4
A17	927775-3	M	1	CuSn4	PRETINNED vorverzinkt min. 0.8µm	0.5-1.0 FLK	2.0-2.7	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.9 K = 4.1 D = 2.4	3	4	5.5	18.8	0.4
A17	927775-1	M	1	CuFe2	PRETINNED vorverzinkt min. 0.8µm	0.5-1.0 FLK	2.0-2.7	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.9 K = 4.1 D = 2.4	3	4	5.5	18.8	0.4
A17	928810-1	A	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	963884-1	A	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927773-3	N	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927773-1	N	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	2-927768-1	R	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	1-927768-1	R	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927768-9	P	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927768-8	P	1	CuFe2	PRETINNED vorverzinkt min. 1µm Spring selective Au Plated	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927768-6	P	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927768-3	P	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927768-1	P	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	1719810-1	A	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	2-927771-2	N	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	2-927771-1	N	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	1-927771-1	N	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927771-9	M	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927771-8	N	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927771-6	M	1	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927771-3	M	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	927771-1	M	1	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.3	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 3.6 K = 3.9 D = 1.8	3.0	4.0	5.5	18.8	0.4
A17	2-927774-1	C	2	CuSn4	PRETINNED vorverzinkt min. 1µm	0.2-0.5 FLR	1.0-1.6	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 2.7 K = 2.8 D = 1.4	2.5	3.5	5.6	18.8	0.4
A17	1-927774-1	C	2	CuFe2	PRETINNED vorverzinkt min. 1µm	0.2-0.5 FLR	1.0-1.6	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 2.7 K = 2.8 D = 1.4	2.5	3.5	5.6	18.8	0.4
A17	927774-6	B	2	CuSn4	PRETINNED vorverzinkt min. 1µm	0.2-0.5 FLR	1.0-1.6	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 2.7 K = 2.8 D = 1.4	2.5	3.5	5.6	18.8	0.4
A17	927774-3	B	2	CuSn4	PRETINNED vorverzinkt min. 1µm	0.2-0.5 FLR	1.0-1.6	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 2.7 K = 2.8 D = 1.4	2.5	3.5	5.6	18.8	0.4
A17	927774-1	B	2	CuFe2	PRETINNED vorverzinkt min. 1µm	0.2-0.5 FLR	1.0-1.6	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 2.7 K = 2.8 D = 1.4	2.5	3.5	5.6	18.8	0.4
A17	963708-1	B	2	CuFe2	PRETINNED vorverzinkt min. 1µm Sonderleitung	0.08-0.2 FLK	1.5-1.8	E = 1.7 G = 1.7 D <sub>Dr</sub> = 0.6	H = 3.1 K = 3.2 D = 1.6	2.5	3.7	5.9	18.8	0.4
A17	969137-1	A	3	CuSn4	PRETINNED vorverzinkt min. 0.8µm	0.2-0.5 FLR	1.2-2.3	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 3.5 K = 3.6 D = 2	2.5	3.5	5	18.8	0.4
A17	1-927778-1	D	3	CuFe2	PRETINNED vorverzinkt min. 0.8µm	0.2-0.5 FLK	1.2-2.3	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 3.5 K = 3.6 D = 2	2.5	3.5	5	18.8	0.4
A17	927778-3	C	3	CuSn4	PRETINNED vorverzinkt min. 0.8µm	0.2-0.5 FLK	1.2-2.3	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 3.5 K = 3.6 D = 2	2.5	3.5	5	18.8	0.4
A17	927778-1	C	3	CuFe2	PRETINNED vorverzinkt min. 0.8µm	0.2-0.5 FLK	1.2-2.3	E = 2.1 G = 2.1 D <sub>Dr</sub> = 0.8	H = 3.5 K = 3.6 D = 2	2.5	3.5	5	18.8	0.4
A17	2112132-1	A	4	CuSn4	PLAIN BLANK	0.2-0.5 FLR	1.15-1.6	E = 2.4 G = 2.3 D <sub>Dr</sub> = 1	H = 2.9 K = 2.9 D = 1.4	2.5	3.5	5.6	18.8	0.2
A17	2-927766-1	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLK	2.7-3.0	E = 3.6 G = 3.8 D <sub>Dr</sub> = 1.8	H = 5.4 K = 4.6 D = 3.2	3.5	5.9	7.5	18.8	0.4
A17	1-927766-1	E	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLK	2.7-3.0	E = 3.6 G = 3.8 D <sub>Dr</sub> = 1.8	H = 5.4 K = 4.6 D = 3.2	3.5	5.9	7.5	18.8	0.4
A17	927766-3	D	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLK	2.7-3.0	E = 3.6 G = 3.8 D <sub>Dr</sub> = 1.8	H = 5.4 K = 4.6 D = 3.2	3.5	5.9	7.5	18.8	0.4
A17	927766-1	D	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLK	2.7-3.0	E = 3.6 G = 3.8 D <sub>Dr</sub> = 1.8	H = 5.4 K = 4.6 D = 3.2	3.5	5.9	7.5	18.8	0.4
A17	2-929937-1	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	1-929937-1	E	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	929937-6	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	929937-3	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	929937-1	E	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	2-929939-1	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	1-929939-1	E	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	929939-6	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	929939-3	E	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	929939-1	E	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	21	0.6
A17	2-927770-1	G	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	18.8	0.6
A17	1-927770-1	G	5	CuFe2	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	18.8	0.6
A17	927770-6	F	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	18.8	0.6
A17	927770-3	F	5	CuSn4	PRETINNED vorverzinkt min. 1µm	0.5-1.0 FLR	1.4-2.1	E = 2.6 G = 2.8 D <sub>Dr</sub> = 1.1	H = 5.4 K = 4.6 D = 3.2	3	5.4	7	18.8	0.6

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Automotive Connectors](#) category:*

*Click to view products by [TE Connectivity](#) manufacturer:*

Other Similar products are found below :

[003-018-000](#) [60403001](#) [60993906-B](#) [M902-2131](#) [M902-2161](#) [M902-2344](#) [72.330.1035.1](#) [73.353.4028.0](#) [F119300-B](#) [F166900](#) [F258300-B](#)  
[F358300-B](#) [F407400](#) [F444110](#) [F487000](#) [F509500B-B](#) [827153-1](#) [8N1515-32-24P](#) [9-1326729-8](#) [925474-1](#) [928905-1](#) [964562-4](#) [968782-1](#)  
[GT17SA-8DS-HU](#) [98891-1012](#) [98947-1016](#) [12004147](#) [12004475-L](#) [12010290](#) [12010309-B](#) [12015454](#) [12020219-B](#) [12041318-B](#) [12052225-](#)  
[L](#) [12052466](#) [12064869](#) [12004327-B](#) [12015308](#) [12015384](#) [12015909](#) [1-21030-1](#) [12041254](#) [12041318](#) [12047946-B](#) [12047957](#) [12047957-L](#)  
[12059473](#) [12066261](#) [12110546](#) [12110546-B](#)