

Analog or Digital Triple Output DC Power Supply

Adjustable 30V/3A
With fixed 5V and 12V outputs

Features:

- 382203 - Analog display
382213 - Digital LCD display
- Triple Output: Adjustable 0-30V, 0-3A plus fixed 5V and 12V
- 0-30V Adjustable Voltage Output
- 0-3A Adjustable Current Output
- Independent 5V and 12V Outputs Provide Power for TTL or CMOS Projects
- Easy Snap Terminals for 5V and 12V outputs
- Overload and Short Circuit Protection
- Constant Voltage or Current
- Current Limiting Front Panel LED Indicator
- Binding Post Terminals for Variable Supply
- Complete with power cord



Specifications	
Voltage Output, DC	0 to 30 Volts
Current Output, DC	0 to 3 Amps
Ripple and Noise	<5mV
Line Regulation	<0.05%+10mV
Load Regulation	<0.05%+10mV
Fixed Output Voltage	5V/0.5A (cont.), 1A(max); 12V/0.5A (cont.), 1A(max)
Display	382203 - Analog or 382213 - Digital (V&A), 3 digit 0.1 res. LCD
Power	110/220VAC 50/60Hz
Dimensions	6 x 5.6 x 9.5" (152 x 142 x 242)
Weight	11lbs. (5kg)

Ordering Information:

- 382203Analog DC Power Supply, 115/220 VAC
 382203-NISTAnalog DC Power Supply, 115/220 VAC with Calibration Traceable to NIST.
 382213Digital DC Power Supply, 115/220 VAC
 382213-NISTDigital DC Power Supply, 115/220 VAC with Calibration Traceable to NIST.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Benchtop Power Supplies](#) category:

Click to view products by [Teledyne FLIR / Extech](#) manufacturer:

Other Similar products are found below :

[NL200](#) [PR20](#) [ZUPNC403](#) [ZUP/W](#) [Z60-7-L-U](#) [ZUPNC402](#) [TL89F2](#) [TL89K1](#) [TL89T1](#) [1332A-NIST](#) [CPX200DP](#) [AX-3003P](#) [AX-6003P](#)
[AX-8450A](#) [TPM-3003](#) [HMC8012](#) [HMP2020](#) [HMP2030](#) [HMP4040](#) [1350](#) [UT804](#) [1410](#) [XLNRC](#) [1513](#) [1514](#) [1550](#) [1651A](#) [1665](#) [1666](#) [1693](#)
[1694](#) [1698](#) [MX100TP](#) [1739](#) [1762](#) [1788](#) [TPM-3005](#) [1902B](#) [9174B](#) [GDM-8245](#) [GDM-8255A](#) [GDM-8341](#) [PSP-603](#) [PSW 160-7.2](#) [QL355P](#)
[SII](#) [HCS-3400-USB](#) [MX180T](#) [MX180TP](#) [382276](#) [1403](#)