



FLIR DM93 True RMS Industrial Multimeter

The new FLIR DM93 is a world-class digital multimeter with advanced VFD filtering to help you accurately analyze non-traditional sine waves and noisy signals found in VFD-controlled equipment.

- VFD Mode filters variable frequency drive signals and provides accurate voltage and frequency measurements during maintenance and troubleshooting
- LoZ Mode eliminates ghost voltage readings associated with long-run applications
- Powerful Worklights eliminate the need for a flashlight while performing tests in dim lighting
- Data Record feature captures electrical measurements and provides wireless data transfer
- Integrated Bluetooth technology* connects the FLIR DM93 to the FLIR Tools Mobile app on your compatible mobile device.
- METERLiNK® technology wirelessly integrates electrical readings on your infrared image with METERLiNK-enabled FLIR Thermal Cameras

Features:

- Voltage and Current, Bright White LED Backlight, Analog Bargraph, Auto AC/DC Voltage, Min, Max, Average Recording, Auto Power Off, Hold, Relative, Peak Hold, Store, Recall

Includes:

- 6 AAA Batteries, User Manual/CD, CAT IV Silicon Test Leads, Type K Temperature Probe (400 °F, 204 °C), Magnetic Hanging Strap and Limited Lifetime Warranty



TECHNICAL SUMMARY	MAX RANGE	BASIC ACCURACY
DC Voltage	1000.0V	±0.05%
AC Voltage	1000.0V	±0.5%
VFD Voltage	1000.0V	±0.5%
DC Current	10.000A	±0.2%
AC Current	10.000A	±1.0%
Resistance	40.00MΩ	±0.2%
Continuity Threshold	30Ω	±0.2%
Frequency	100.00kHz	±5 Digits
Capacitance	40.00mF	±0.9%
Temperature	-328 to 2192°F, -200 to 1200°C	±1.0%
Diode Test	2V	±1.5%

* See www.flir.com/test for latest compatibility information and more warranty details



GENERAL INFORMATION	
Bluetooth Range Max	32 ft (10 m)
Display Counts	40,000
Category Rating	CAT IV-600V, CAT III-1000V
Data Recording	20,000 Pts (125 days max)
Warranty	Limited Lifetime*

Ordering Information

DM93 True RMS Industrial Multimeter with VFD Mode
 DM93-NIST..... DM93 with Certificate of Traceability to NIST
 TA80..... CAT IV Silicon Test Leads



NASHUA
 FLIR Systems, Inc.
 PH: +1 603-324-7600

PORTLAND
 Corporate Headquarters
 FLIR Systems, Inc.
 PH: +1 866.477.3687

CANADA
 FLIR Systems, Ltd.
 PH: +1 800.613.0507

MEXICO/LATIN AMERICA
 FLIR Systems Brasil
 Av. Antonio Bardella
 PH: +55 15 3238 8070

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Digital Multimeters](#) category:

Click to view products by [Teledyne FLIR / Extech](#) manufacturer:

Other Similar products are found below :

[6111-517](#) [FS881](#) [C.A 6133 LAUNCH KIT](#) [P 1020 A](#) [P 1070](#) [P 3315](#) [P 3340](#) [KEWMATE 2000A](#) [P 3725](#) [SEFRAM7202](#) [SEFRAM7303](#)
[AMP-220-EUR KIT2](#) [BS K-CLIP](#) [P 2005 A](#) [19290](#) [IBT6K](#) [AX-573](#) [C.A 5293-BT](#) [1000-219](#) [1001-613](#) [1006-969](#) [30XR](#) [34XR](#) [35XP](#)
[TESTO 745](#) [0590 7450](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-594](#) [AX-](#)
[LCR42A](#) [AX-MS811](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM805S](#) [BM807S](#) [BM817S](#) [BM827S](#)
[BM829S](#) [BM857S](#) [BM859S](#)