

PT400 Programmable Timer



The Extech PT400 provides flexible energy-saving solutions for your day-to-day use of appliances in the home or office. It features three selectable power settings (Manual ON, Manual OFF, and Auto), ten customizable ON/OFF programs, and sixteen program combinations for individual days, weekends, week, and more. It simultaneously displays time of day (12/24 hour format), day of the week, and the currently-selected program. It also has Daylight Savings mode, randomize program function, and countdown timer. Design includes standard North American 3-prong electrical plug, side-socket connection for ease-of-use, and rechargeable backup battery that saves customized programs in the event of a power outage.



Features

- LCD displays time, day and program function
- Program time resolution is 1 minute
- Sixteen Program combinations for individual days or Mon-Fri, Mon-Sun, Sat-Sun, Mon-Sat, Mon/Weds/Fri, Tues/Thurs/Sat, Mon/Tues/Weds, Thurs/Fri/Sat, Mon/Weds/Fri/Sun
- Easy to install and operate
- Programmable countdown function from 99 hours, 59 minutes and 59 seconds
- Random Function
- 12/24 hour mode with Daylight Savings Time function
- Rechargeable battery backup (>100 hours)
- Standard North American (Type B) 3-prong plug and front socket for easy connection

Specifications

Switching Capacity	15A General Purpose or Resistive Load; 10A Tungsten, 1/2 HP, TV-5
Power	125V AC, 60Hz
Switch Settings	10 On/Off Programs
Switching Interval	1 minute minimum On/Off time
Random Function	Switches on randomly for 10 to 31 minutes between 6:00PM and 6:00AM
Dimensions	2.57 x 2.67 x 2.4" (65.3 x 67.8 x 61mm)
Weight	4 oz (113.4g)

Ordering

PT400 Programmable Timer

Note: Designed with a standard North American (Type B) 3-prong plug and side socket connector



UPC Code: 793950234006

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Timers](#) category:

Click to view products by [Teledyne FLIR / Extech](#) manufacturer:

Other Similar products are found below :

[79237785](#) [H5AN-4DM DC12-24](#) [H5CN-YAN AC100-240](#) [H5CX-L8S-N AC100-240](#) [H5AN-4D DC12-24](#) [THR2U-110A](#) [81506944](#)
[88225029](#) [H5S-YB4-X](#) [H7AN-2D DC12-24](#) [H5CN-XANS DC12-48](#) [H7AN-W4DM DC12-24](#) [H7AN-4DM DC12-24](#) [H7AN-4D DC12-24](#)
[H7AN-RT6M AC100-240](#) [600DT-CU](#) [7PV1513-1AP30](#) [7PV1538-1AW30](#) [1SVR508020R0000](#) [1SVR508020R1100](#) [1SVR508100R0000](#)
[1SVR550127R4100](#) [1SVR550212R4100](#) [1SVR730010R3200](#) [1SVR730020R3300](#) [1SVR730120R3100](#) [1SVR730180R3100](#)
[1SVR730210R3300](#) [1SVR730211R2300](#) [PCU-511UNI](#) [H3C-R](#) [H3CR-A8-301 24-48AC/12-48DC](#) [H3CR-A8E 24-48AC/DC](#) [H3CR-F8 100-](#)
[240AC/100-125DC](#) [H3CR-FN 100-240AC/100-125DC](#) [H3DK-G 24-230AC/DC](#) [H3DK-HBL AC/DC24-48](#) [H3DK-M1A DC12](#) [LT4H-AC24V](#)
[LT4HW8-AC240V](#) [LT4HW-AC240V](#) [LT4HW-AC24VS](#) [LT4HW-DC24V](#) [31L48AP](#) [31L48TPM240](#) [RC302](#) [RC312](#) [REV-201M](#) [RG](#)
[AT78041](#)