

SD900 3-Channel DC Current Datalogger



SD Card Included

Extech's SD900 allows technicians to easily monitor and record DC mA values from 3 external sensors, transducers, and other sources using one meter. It also stores the time and date of when readings are taken. The logger features a large triple LCD display and records data on an SD card in an Excel[®]-ready format for easy transfer to a PC for analysis, trending, and archiving.

Applications:

- pH recording
- 4 to 20mA recording
- Low Level Signal Monitoring
- Photovoltaic Studies
- Battery Studies
- Process Control
- R&D
- Medical/Pharmaceutical
- Environmental Studies



Features

- Triple LCD simultaneously displays three DC Current (mA) channels
- Datalogger date/time stamps and stores readings on an SD card in Excel[®] format for easy transfer to a PC
- User can select the data sampling rate: 2, 5, 10, 30, 60, 120, 300, 600 seconds or Auto
- Complete with six AAA batteries, SD memory card, Universal AC Adaptor with multi-plugs (US, EU, UK, AUS), 3 input connect sockets, and mounting bracket

Specifications	Range	Max. Resolution	Basic Accuracy (%rdg +digits)
DC mA Current	0 to 20mA	0.01mA	±(0.5% + 0.02mA)
Memory	Approx. 2.7M readings using 4GB SD memory card		
Dimensions	5.2 x 3.1 x 1.3" (132 x 80 x 32mm)		
Weight	7oz (199g)		

Ordering

SD900..... 3-Channel DC Current Datalogger



UPC Code: 793950439005

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Data Logging & Acquisition](#) category:

Click to view products by [Teledyne FLIR / Extech](#) manufacturer:

Other Similar products are found below :

[PCI-6208A](#) [DAQe-2502](#) [ACL-8112DG](#) [SpotBotBLE](#) [MCM-204](#) [DAQM909A](#) [ACL-7130](#) [LPCI-7230](#) [PXES-2780](#) [Rack-Mount kit](#) [USB-4761-BE](#) [SE028](#) [PCI-1711UL-CE](#) [USB-4702-AE](#) [USB-4704-AE](#) [USB-4716-AE](#) [USB-4750-BE](#) [USB-4751-AE](#) [USB-4751L-AE](#) [PCI-1710UL-DE](#) [PCI-1710U-DE](#) [PCI-1710HGU-DE](#) [AR207/8/S1/PPPP/IP30](#) [U2781A](#) [4610](#) [EL-USB-5](#) [AR407/S1/P/P/P/P](#) [AR207/8/S2/PPPP/IP30](#) [ACL-8112PG](#) [cPCI-7248](#) [cPCI-7433](#) [DAQ-2204](#) [DAQ-2501](#) [ND-6024](#) [ND-6053](#) [ND-6060](#) [ND-6063](#) [PCI-7230](#) [PCI-7432](#) [PCI-9112](#) [PCI-9112A](#) [PCI-9113A](#) [PCI-9221](#) [PCM-7248+](#) [USB-1902](#) [USB-1903](#) [MIC-1810-U0A1E](#) [PCIE-1813-AE](#) [USB-5862-AE](#) [AR654/S1/P/P/P/P/IP30](#) [AR654/S2/P/P/P/P/IP30](#)