

CH0002

Technical Datasheet



Features

- LED status indicator
- Contains charger, universal power supply and line cord

Benefits

- Specifically designed to charge Ultralife UBI-2590 battery family (UBBL02, UBBL10 and UBBL13) safely & efficiently
- Safety circuit protects against charging shorted packs

Applications

- Commercial desktop charger for UBI-2590 battery family

Technical Specifications

Part No.	CH0002
DC Input	19-40VDC
DC Output	16.8V
Charge Rate	1.7A
Battery Types	Li-Ion
User Interface	Off: No battery detected Green Blinking: Charging Green Steady On: Charge complete Red Blinking: Error
Connectors	Input: 2.5mm Center Positive
Color	Black
Finish	Case Material: ABS G1SM
Size	Charger: 174mm (6.85in) x 124mm (4.88in) x 54mm (2.12in) Charger Cable: 60.9cm (24in)
Weight	460g (16.2oz)
Operating Temperature	0°C to 45°C
Storage Temperature	-25°C to 70°C
Accessories Included	Power Supply - PS2524 Input Voltage: 100-240VAC, 47-63Hz Output Voltage: 24VDC Input Connector: IEC-320 Output Cable: 18Awg, 1.83m (6ft) Weight: 300g (10.5oz) Line Cord - UL/CSA 3 prong (North America), length 1.83m (6ft)
Accessories Optional	CA0003 - Vehicle Power Adapter Line Cords: USA: 1090-01-0002 AUS: 1090-01-0004 EUR: 1090-01-0008

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Battery Chargers](#) category:

Click to view products by [Ultralife](#) manufacturer:

Other Similar products are found below :

[CH0011](#) [CB1210A](#) [PS-034052](#) [GP X411 AA/AAA + 4X R6 2700MAH RECYKO](#) [CB123A](#) [CB12245A](#) [DA60U-240A-R](#) [DA84U-240A-R](#)
[DA200U-250A-R](#) [MC2](#) [MC1](#) [BQ-CC55E](#) [VP4 PLUS DRAGON](#) [LCD MULTI CHARGER](#) [MINI-CHARGER](#) [5V 2.1A](#) [PB320](#) [PB50](#)
[PB550 + 4XAA 2700MAH](#) [VC4](#) [POCKET-CHARGER + 4XAA 2100MAH](#) [PB-300P-12](#) [VC2](#) [MINI CHARGER + 2XAA 2100MAH](#)
[CHFC3](#) [GC30U-5P1J](#) [TSP-BCM48](#) [SBP-001](#) [PB-300N-12](#) [GC30B-11P1J](#) [GC220A12-AD1](#) [DBU-3200-24](#) [RRC-SMB-MBC](#) [PSC-122000A-](#)
[C](#) [TSP-BCM12](#) [TSP-BCM360](#) [TSP-BCM48A](#) [H-TRONIC AL 2000PLUS](#) [H-TRONIC HTDC 5000](#) [ES360A](#) [LS-CR45-PQ](#) [LS-CR45-PD](#)
[WHITE](#) [5V 1A](#) [MC3](#) [PB2 BLUE](#) [SC1](#) [SC2](#) [VC2S](#) [X2](#) [X4](#)