


Item no.: 770-104  
 Product description: socket with relief housing 4 pole pin spacing 10 mm / 0.394 in  
 100% protected against mismatching wire diameter 9-13 mm



Produkt kann von Bild abweichen / product may differ

Packing unit 25 pieces

RoHS compliant

Product group	20 (WINSTA)
pole count	4
Cross section [mm <sup>2</sup> ]	0.5 - 4 mm <sup>2</sup>
Cross section [AWG]	20 - 12 AWG
Connection method	CAGE CLAMP®S Connection
Measured voltage EN	400 V
Measured shock voltage	6 kV
Pollution degree	3
Current intensity EN	25 A
Weight	24.542 g
Color	black
No. of connection Points	8
No. of potentials	4
Height	17 mm
Height	0.669 in
Width	44.6 mm
Width	1.756 in
Depth	75.9 mm
Depth	2.988 in

Strip length from  
Strip length to  
Strip length

9 mm  
9 mm  
0.35 in



Item number	Admission office	Approval no.	Voltage [V]	Current [A]	Cross section [ mm <sup>2</sup> ]
770-104	ABS	06-HG154986/11-PDA	400	25	0,5-4,0
770-104	CBCertificateVDE	DE1-29543	250/400	25	0,5-4
770-104	CCA		400	25	0,5-4,0
770-104	cURus	E45171	600	20	12
770-104	DNV	E-9217	400	25	4
770-104	GL	42875-02HH	400	25	4
770-104	KEMA		400	25	0,5-4,0
770-104	LR	02/20050(E3)	250	25	2,5
770-104	PRS	TE/1719/880590/08	400	25	0,5-4,0
770-104	PSE	JET0695-43009-1002	600	20	12
770-104	VDE	Ausweis.Nr.30726	250/400	16/25	0,5-4,0

Sorting criteria: admission office - approval number

© WAGO Kontakttechnik GmbH & Co. KG

Specifications are subject to changes and errors may be expected

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Wago manufacturer](#):*

Other Similar products are found below :

[0207-1331](#) [0207-1332](#) [0207-1333](#) [0233-0505](#) [0233-0506](#) [0233-0510](#) [0233-0524](#) [0236-0404](#) [0256-0402](#) [0256-0403](#) [0256-0404](#) [0256-0405](#)  
[0256-0406](#) [0256-0408](#) [0280-0681](#) [0280-0687](#) [0280-0833](#) [0280-0907](#) [0281-0611](#) [0281-0611/0281-0418/RN01-0000](#) [0281-0623](#) [0281-](#)  
[0623/0281-0418/RN01-0000](#) [0281-0681](#) [0281-0907](#) [0282-0402](#) [0282-0681](#) [0282-0687](#) [0282-0696](#) [0282-0901](#) [0283-0402](#) [0283-0671](#) [0283-](#)  
[0901](#) [0285-0635](#) [0721-0104/0026-0000/RN01-0000](#) [0733-0102](#) [0733-0108](#) [0733-0110](#) [0733-0112](#) [0745-0302](#) [145-261](#) [2000-1201](#) [2000-](#)  
[1203](#) [2000-1204](#) [2000-1205](#) [2000-1207](#) [2000-1291](#) [2000-1292](#) [2000-1307](#) [2000-1401](#) [2000-1403](#)