

7447 Kraftform pistol grip, adjustable torque screwdrivers with Rapidaptor quick-release chuck, 1/4 inch, 25,0 - 55,0 in. lbs.
Adjustable torque screwdrivers



EAN	4013288102904	Dimension:	150x100x36.5 mm
Code:	05074712001	Weight:	280 g
Article-No.		Country of origin:	CZ
		Customs tariff no.:	82054000

- Adjustable Kraftform torque screwdriver with pistol handle and Rapidaptor quick-release chuck
- Suitable for bits with 1/4" hex head drive
- Rapidaptor technology for rapid bit change
- Distinct signal when pre-set value is reached
- Numerical torque value indicator

Wera torque screwdriver. Kraftform pistol handle for particularly high torque transfer, multi-component for high working speeds and particularly ergonomic screwdriving. Variable torque setting option with highest precision. Simple adjustment of the required torque value without any special tools. Easy-to-read scale value. Rapidaptor quick-release technology for rapid bit change. Unlimited torque to loosen seized screws. Multi-component Kraftform handle with hard and soft zones for high working speeds, whilst being easy on the hand. Suitable for bits with 1/4 hexagon head drive as per DIN ISO 1173-C 6.3 and E 6.3 (ISO 1173)."

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Wera](#) manufacturer:

Other Similar products are found below :

[05118014001](#) [05006100001](#) [05073670001](#) [05059515001](#) [KRAFTFORM KOMPAKT VARIO RA](#) [KRAFTFORM KOMPAKT VDE 60I](#)
[3.0MM](#) [KRAFTFORM KOMPAKT 60IS/65IS/67IS/16](#) [JOKER SET 6TLG 1 METRISCH 160 I/7](#) [05018500001](#) [05118048001](#) [7436 ESD](#)
[30,0 - 100,0 NCM](#) [22820](#) [7451 ESD 30,0 NCM](#) [8735](#) [002990](#) [KRAFTFORM KOMPAKT ZYKLOP 1/4"](#) [118030](#) [117990](#) [190I 3K SW 5,5 X](#)
[125 MM](#) [932/6](#) [05052490001](#) [05030410001](#) [05030082001](#) [05006156001](#) [05059636001](#) [167I 3K TX 45 X 150 MM](#) [05031606001](#)
[05135906001](#) [05074705001](#) [8100 SA4](#) [05004970001](#) [05024466001](#) [05024467001](#) [05024469001](#) [05003881001](#) [05003972001](#) [05104652001](#)
[05133355001](#) [05003439001](#) [05057908001](#) [8767](#) [8790 4.0](#) [8790 5.0](#) [8790 8.0](#) [8790 10.0](#) [05073640001](#) [05134380001](#) [05073285001](#)
[05073286001](#)