

# 169 MHz Antenna

## Key Features

- 169 MHz
- Bendable whip
- SMA/m connector

## Description



The WIRL-ACCE 2600130011 is a robust antenna for 169 MHz applications. The antenna has a SMA/m connector. The antenna is equipped with a bendable whip.

Because of the antenna technology a ground plane is needed. The antenna is optimized to work with a square ground plane of 30 x 30 cm.



## Range of Application

2600130011 is well suited for all 169 MHz applications where good radio performance is needed as for example in metering applications.

## Specification

Part number	2600130011
Frequency	169 MHz
VSWR	< 2:1
Gain	max. 1 dBi
Height	320 mm
Diameter	15 mm
Weight	42 g
Connector	SMA male
Temperature	-40 to +85°C
Ingress Protection	IP65

## Ordering Information

Item no.	Description
2600130011	Antenna 169 MHz



**Würth Elektronik eiSos GmbH & Co.KG**  
 Phone +49 7942 945 0  
 Email [wireless-sales@we-online.com](mailto:wireless-sales@we-online.com)  
 Internet [www.we-online.com](http://www.we-online.com)

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Antennas](#) category:*

*Click to view products by [Wurth](#) manufacturer:*

Other Similar products are found below :

[GAN30084EU](#) [930-033-R](#) [GW17.07.0250E](#) [1513563-1](#) [EXE902SM](#) [APAMPG-117](#) [MAF94383](#) [W3908B0100](#) [W6102B0100](#) [YE572113-30RSMM](#) [108-00014-50](#) [66089-2406](#) [SPDA17RP918](#) [A09-F8NF-M](#) [A09-F5NF-M](#) [RGFRA1903041A1T](#) [W3593B0100](#) [W3921B0100](#) [SIMNA-868](#) [SIMNA-915](#) [SIMNA-433](#) [W1044](#) [W1049B090](#) [A75-001](#) [WTL2449CQ1-FRSMM](#) [CPL9C](#) [EXB148BN](#) [0600-00060](#) [TRA9020S3PBN-001](#) [GD5W-28P-NF](#) [MA9-7N](#) [GD53-25](#) [GD5W-21P-NF](#) [C37](#) [MAF94051](#) [MA9-5N](#) [EXD420PL](#) [B1322NR](#) [QWFTB120](#) [MAF94271](#) [MAF94300](#) [GPSMB301](#) [FG4403](#) [AO-AGSM-OM54](#) [5200232](#) [MIKROE-2349](#) [WCM.01.0111](#) [MIKROE-2393](#) [MIKROE-2352](#) [MIKROE-2350](#)