

868 MHz Antenna

Key Features

- 868 MHz
- Dipole Antenna
- SMA/m connector

Description



The WIRL-ACCE 2600130081 is a robust antenna for 868 MHz applications. The articulating base allows the antenna to tilt 90 degrees and rotate 360 degrees. The antenna has a SMA/m connector.

Because of the antenna technology, the dipole design, no additional ground plane is required.

Range of Application

2600130081 is well suited for all 868 MHz applications where good radio performance is needed as for example in industrial & monitoring applications as well as in metering applications.

Specification

Part number	2600130081
Frequency	868 MHz (853 to 883 MHz)
VSWR	< 2.0
Gain	max. -2.3 dBi
Height	142 mm
Diameter	10 mm
Weight	14.3g
Connector	SMA male
Temperature	-30 to +80°C
Impedance	50 Ohms

Ordering Information

Item no.	Description
2600130081	Antenna 868 MHz



Würth Elektronik eiSos GmbH & Co.KG

Phone +49 7942 945 0

Email wireless-sales@we-online.com

Internet www.we-online.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Antennas](#) category:

Click to view products by [Wurth](#) manufacturer:

Other Similar products are found below :

[GAN30084EU](#) [930-033-R](#) [GW17.07.0250E](#) [1513563-1](#) [EXE902SM](#) [APAMPG-117](#) [MAF94383](#) [W3908B0100](#) [W6102B0100](#) [YE572113-30RSMM](#) [108-00014-50](#) [66089-2406](#) [SPDA17RP918](#) [A09-F8NF-M](#) [A09-F5NF-M](#) [RGFRA1903041A1T](#) [W3593B0100](#) [W3921B0100](#) [SIMNA-868](#) [SIMNA-915](#) [SIMNA-433](#) [W1044](#) [W1049B090](#) [A75-001](#) [WTL2449CQ1-FRSMM](#) [CPL9C](#) [EXB148BN](#) [0600-00060](#) [TRA9020S3PBN-001](#) [Y4503](#) [GD5W-28P-NF](#) [MA9-7N](#) [GD53-25](#) [GD5W-21P-NF](#) [C37](#) [MAF94051](#) [MA9-5N](#) [EXD420PL](#) [B1322NR](#) [QWFTB120](#) [MAF94271](#) [MAF94300](#) [GPSMB301](#) [FG4403](#) [AO-AGSM-OM54](#) [5200232](#) [MIKROE-2349](#) [WCM.01.0111](#) [MIKROE-2393](#) [MIKROE-2352](#)