



SOLDER SUFFIX	CUSTOMER TERMINAL	RoHS	LEAD(Pb)-FREE
LF1	Sn96%, Ag4%	Yes	Yes


more than you expect




TERM. NO.'s FOR REF. ONLY



DOT LOCATES TERM. #1
LOT CODE & DATE CODE
SOLDER SUFFIX



AREA REPRESENTS TERMINAL PAD DIMENSIONS



ELECTRICAL SPECIFICATIONS @ 25°C unless otherwise noted:

PARAMETER	TEST CONDITIONS	VALUE
D.C. RESISTANCE	3-1 @20°C	0.062 ohms ±20%
D.C. RESISTANCE	4-5 @20°C	0.425 ohms ±20%
D.C. RESISTANCE	8-6 @20°C	0.006 ohms ±20%
D.C. RESISTANCE	10-9 @20°C	0.019 ohms ±20%
INDUCTANCE	3-1 100kHz, 100mVAC, Ls	37uH ±10%
LEAKAGE INDUCTANCE	3-1 tie(6+8), 100kHz, 100mVAC, Ls	3.5uH typ., 5uH max.
DIELECTRIC	3-8 1500VDC, 1 second	-
DIELECTRIC	3-10 1500VDC, 1 second	-
DIELECTRIC	4-8 1500VDC, 1 second	-
DIELECTRIC	4-10 1500VDC, 1 second	-
DIELECTRIC	3-4 500VDC, 1 second	-
URNS RATIO	(3-1):(8-6)	5.25:1, ±2%
URNS RATIO	(3-1):(10-6), tie(8+9)	3.5:1, ±2%
URNS RATIO	(3-1):(4-5)	1.91:1, ±2%

DETAILS SUBJECT TO CHANGE

REV.	DATE	Packaging Specifications Method: Tape & Reel PKG-0499 www.we-online.com/midcom		Tolerances unless otherwise specified: Angles: ±1° Decimals: ±.005 [.13] Fractions: ±1/64 Footprint: ±.005 [.13]	DRAWING TITLE TRANSFORMER	PART NO. 32395R-LF1
6C	2/12					
6B	10/07					
6A	7/06	SEE REVISION SHEET FOR REVISION LEVEL		This drawing is dual dimensioned. Dimensions in brackets are in millimeters.	eiSos p/n: 750032395	compliant RoHS SPECIFICATION SHEET 1 OF 1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Power Transformers](#) category:

Click to view products by [Würth](#) manufacturer:

Other Similar products are found below :

[ET-030A](#) [F-102X](#) [F-120X](#) [F-14X-1](#) [F-181U](#) [F-18A](#) [F-199U](#) [F-19X](#) [F-202U](#) [F-204U](#) [F-206U](#) [F-227X](#) [F-238U](#) [F-239U-1](#) [F-23U](#) [F24-250-B](#)
[F-242U](#) [F-245U](#) [F-264U](#) [F-265U](#) [F-267U](#) [F-281U](#) [F-283U](#) [F-290X](#) [F-295Z](#) [F-296Z](#) [F-298Z](#) [F-3143P](#) [F-3298Z](#) [F-33U](#) [F-346X](#) [F-35U](#) [F-](#)
[364U](#) [F-392A](#) [F-395X](#) [F-397U](#) [F-412X](#) [F-47U](#) [F-55X-1](#) [F-60U](#) [F-68U](#) [F-71U](#) [F-72Z](#) [F-74U](#) [F-83A](#) [F-84AC](#) [F-85U](#) [F-86U](#) [F-9U](#) [PCT-02](#)