



CUSTOMER TERMINAL	RoHS	LEAD(Pb)-FREE
Sn96%, Ag4%	Yes	Yes



more than you expect



TERM. NO.'s FOR REF. ONLY



DOT LOCATES TERM. #1
LOT CODE & DATE CODE




ELECTRICAL SPECIFICATIONS @ 25°C unless otherwise noted:

PARAMETER	TEST CONDITIONS	VALUE
D.C. RESISTANCE	1-2 @20°C	0.250 ohms ±10%
D.C. RESISTANCE	3-4 @20°C	0.180 ohms ±10%
D.C. RESISTANCE	6-7 @20°C	0.017 ohms max.
D.C. RESISTANCE	9-10 @20°C	0.105 ohms ±10%
INDUCTANCE	3-4 100kHz, 100mVAC, Ls	127.0uH ±10%
LEAKAGE INDUCTANCE	3-4 tie(1+2, 6+7, 9+10) 100kHz, 100mVAC, Ls	1.2uH max.
DIELECTRIC	1-6 1875VAC, 1 second	1500VAC, 1 minute
DIELECTRIC	1-10 1875VAC, 1 second	1500VAC, 1 minute
DIELECTRIC	4-6 1875VAC, 1 second	1500VAC, 1 minute
DIELECTRIC	4-10 1875VAC, 1 second	1500VAC, 1 minute
TURNS RATIO	(3-4):(6-7)	6:1, ±1%
TURNS RATIO	(3-4):(9-10)	1.764:1, ±1%
TURNS RATIO	(3-4):(2-1)	1.764:1, ±1%

GENERAL SPECIFICATIONS:

OPERATING TEMPERATURE RANGE: -40°C to +125°C.

REV.	DATE	Packaging Specifications
		Method: Tape & Reel PKG-0499 www.midcom-inc.com
6A	12/07	SEE REVISION SHEET FOR REVISION LEVEL



CONVENTION PLACEMENT

Tolerances unless otherwise specified:
Angles: ±1° Decimals: ±.005 [.13]
Fractions: ±1/64 Footprint: ±.005 [.13]

This drawing is dual dimensioned. Dimensions in brackets are in millimeters.

DRAWING TITLE

TRANSFORMER

eiSos p/n: 750310007

PART NO.

750310007



SPECIFICATION SHEET 1 OF 1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Power Transformers](#) category:

Click to view products by [Würth](#) manufacturer:

Other Similar products are found below :

[ET-030A](#) [F-102X](#) [F-120X](#) [F-14X-1](#) [F-181U](#) [F-18A](#) [F-199U](#) [F-19X](#) [F-202U](#) [F-204U](#) [F-206U](#) [F-227X](#) [F-238U](#) [F-239U-1](#) [F-23U](#) [F24-250-B](#)
[F-242U](#) [F-245U](#) [F-264U](#) [F-265U](#) [F-267U](#) [F-281U](#) [F-283U](#) [F-290X](#) [F-295Z](#) [F-296Z](#) [F-298Z](#) [F-3143P](#) [F-3298Z](#) [F-33U](#) [F-346X](#) [F-35U](#) [F-](#)
[364U](#) [F-392A](#) [F-395X](#) [F-397U](#) [F-412X](#) [F-47U](#) [F-55X-1](#) [F-60U](#) [F-68U](#) [F-71U](#) [F-72Z](#) [F-74U](#) [F-83A](#) [F-84AC](#) [F-85U](#) [F-86U](#) [F-9U](#) [PCT-02](#)