

CUSTOMER TERMINAL	RoHS	LEAD(Pb)-FREE
Sn96%, Ag4%	Yes	Yes






ELECTRICAL SPECIFICATIONS @ 25°C unless otherwise noted:

PARAMETER	TEST CONDITIONS	VALUE
D.C. RESISTANCE	2-4 @20°C	0.240 ohms ±10%
D.C. RESISTANCE	7-8 @20°C	3.50 ohms ±10%
D.C. RESISTANCE	9-10 @20°C	0.470 ohms ±10%
D.C. RESISTANCE	11-12 @20°C	1.35 ohms ±10%
INDUCTANCE	2-4 10kHz, 100mVAC, Ls	120uH ±10%
SATURATION CURRENT	2-4 20% rolloff from initial	650mA
LEAKAGE INDUCTANCE	2-4 tie(7+8+9+10+11+12), 100kHz, 100mVAC, Ls	2.5uH typ., 5.0uH max.
DIELECTRIC	2-7 tie(8+9+11), 625VAC, 1 second	-
DIELECTRIC	7-12 tie(8+9), 625VAC, 1 second	-
DIELECTRIC	7-10 625VAC, 1 second	-
TURNS RATIO	(7-8):(2-4)	3:1, ±1%
TURNS RATIO	(2-4):(9-10)	1.77:1, ±1%
TURNS RATIO	(2-4):(11-12)	1.77:1, ±1%

GENERAL SPECIFICATIONS:

OPERATING TEMPERATURE RANGE: -40°C to +125°C including temp rise.

Functional insulation only.



Wire insulation & RoHS status not affected by wire color.
Wire insulation color may vary depending on availability.

REV.	DATE	Packaging Specifications Method: Tape & Reel PKG-0757 www.we-online.com/midcom		Tolerances unless otherwise specified: Angles: ±1° Fractions: ±1/64 Decimals: ±.005 [.13] Footprint: ±.005 [.13]	DRAWING TITLE TRANSFORMER	PART NO. 750315856
6B	11/18	SEE REVISION SHEET FOR REVISION LEVEL		This drawing is dual dimensioned. Dimensions in brackets are in millimeters.	eiSos p/n: 750315856	
6A	4/16					SPECIFICATION SHEET 1 OF 1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Power Transformers](#) category:

Click to view products by [Würth](#) manufacturer:

Other Similar products are found below :

[ET-030A](#) [F-102X](#) [F-120X](#) [F-14X-1](#) [F-181U](#) [F-18A](#) [F-199U](#) [F-19X](#) [F-202U](#) [F-204U](#) [F-206U](#) [F-227X](#) [F-238U](#) [F-239U-1](#) [F-23U](#) [F24-250-B](#)
[F-242U](#) [F-245U](#) [F-264U](#) [F-265U](#) [F-267U](#) [F-281U](#) [F-283U](#) [F-290X](#) [F-295Z](#) [F-296Z](#) [F-298Z](#) [F-3143P](#) [F-3298Z](#) [F-33U](#) [F-346X](#) [F-35U](#) [F-](#)
[364U](#) [F-392A](#) [F-395X](#) [F-397U](#) [F-412X](#) [F-47U](#) [F-55X-1](#) [F-60U](#) [F-68U](#) [F-71U](#) [F-72Z](#) [F-74U](#) [F-83A](#) [F-84AC](#) [F-85U](#) [F-86U](#) [F-9U](#) [PCT-02](#)