









RoHS Compliant



### Dimensions (In.)



### ■ SPECIFICATIONS

- Impedance variation:  $\pm 10\%$  @ 1KHz
- DC Resistance tolerance:  $\pm 15\%$
- Insulation:  $>10M\Omega$  @ 100VDC
- Core type / size: EI-14
- Breakdown voltage: 100VAC Hipot for 1 minute
- Waxing: Vacuum treatment can be water washed with water temperature less than  $20^{\circ}C$
- Max output: 75mW
- Freq. response:  $\pm 3dB$ , 300Hz-3.5 KHz @ 1KHz 0dB
- Can be water washed with water temperature less than  $20^{\circ}C$
- RoHS Compliant

Mouser Stock No.	Impedance		Resistance	
	PRI	SEC	PRI	SEC
42XL001-RC	500 $\Omega$	8 $\Omega$	35 $\Omega$	1 $\Omega$
42XL002-RC	10K $\Omega$	2K $\Omega$	580 $\Omega$	200 $\Omega$
42XL003-RC	1.2K $\Omega$	8 $\Omega$	80 $\Omega$	1 $\Omega$
42XL009-RC	500 $\Omega$	500 $\Omega$	40 $\Omega$	38 $\Omega$
42XL016-RC	600 $\Omega$	600 $\Omega$	65 $\Omega$	55 $\Omega$
42XL031-RC	600 $\Omega$	100 $\Omega$	74 $\Omega$	28 $\Omega$

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Audio Transformers](#) / [Signal Transformers](#) category:*

*Click to view products by [Xicon](#) manufacturer:*

Other Similar products are found below :

[CX2041NLT](#) [MGPWT-00449-P](#) [PE-64961](#) [H1302FNLT](#) [H5008FNL](#) [H5012FNL](#) [H5020FNLT](#) [H5077NLT](#) [H5079NLT](#) [H5084FNLT](#)  
[B78476A9558A003](#) [1812WBT2-4](#) [1879479-1](#) [HX2260FNL](#) [HX5014FNL](#) [EX2024FNL](#) [FL1066](#) [T1137NLT](#) [T3012NL](#) [PE-65812FNL](#) [PE-65848FNLT](#) [H1174FNL](#) [H1302FNL](#) [H5015FNL](#) [H5019EFNL](#) [H5062FNLT](#) [CX2047LNL](#) [MGPWT-00059-P](#) [MGPWT-00266-P](#) [MGPWT-00278-P](#) [MGPWT-00431-P](#) [TTC-100](#) [TTC-143-H](#) [TTC-5032-1](#) [BX1194WNLT](#) [HX1234NLT](#) [HX5008FNLT](#) [HX5019FNL](#) [HX5084NL](#) [3-1879385-5](#) [TX1263NLT](#) [4-1879391-0](#) [T1142NL](#) [HX6101FNL](#) [HX5084FNL](#) [HX1148NL](#) [HX5020FNLT](#) [HX5014FNLT](#) [T1124NL](#)  
[1879732-1](#)