



Recommended P.C.B
Layout(±0.05)

XKB Connectivity

Technical Data
 Pin(outer sleeve):Brass,machined CuZn38Pb2
 ClIp(Contact 4 FInger):Beryllium copper,heat teated
 Insulator:PPS UL94V-0 colour:black
 Current rating:3Amps
 Mating pin Ø:0.635/0.889mm
 Forces:(polished steel gaugeØ0.43mm)
 -Insertion:2N typ
 -Withdrawal:1N typ
 Mechanical life:min 500cycles
 Contact resistance:max 10m Ω
 Dielectric strength:min 1000V RMS
 Operating temperature:-40°C to+105°C
 Soldering temperature:+255°C

XKB Connectivity

X5521 F V-2xXX -C42D32- 7400
 ① ②③④ ⑤ ⑥ ⑦

- ① Series.N0.
- ② Category : F-Female
- ③ Welding Board Angle : V-straight 180°
- ④ Row No-Pin No:2xXX-2x01P-2xXXP
- ⑤ Pin Length :C=4.2mm
- ⑥ Pin Length :D=3.2mm
- ⑦ 7400:Type7400

XKB Connectivity

X5521FV-2xXX-C42D32-7400	PPS 94V-0	Brass	Tin Gold 1u"	X5521W
PART NO	Material	Material(Terminal)	Finish(Terminal)	Mates With XKB Pin Header

						DSND		DATE		SCALE: N/A	MODEL TYPE: X5521FV-2xXX-C42D32-7400			
						ANGLAR				VIEW:	PART NO.:			
Δx					L ≤ 4	±5°								
Δx					4 < L ≤ 16	±0.2								
Δx					16 < L ≤ 63	±0.3	CHKD	DATE	UNIT: mm/in		DWG NO.:			
MARK	DESCRIPTION	DATE	REVISED	APPROVED	L > 63	±0.4	APPD	DATE	SIZE: A4					
REVISIONS						UNSPECIFIED TOLERANCES	XKB INDUSTRIAL PRECISION CO.,LIMITED				WEIGHT 1.0g	SHEET 1/1	REVISION A0	
www.xk-dg.cn www.helloxkb.com www.helloxkb.cn														

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [XKB](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [009176003701906](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [644827-2](#) [65495-038](#) [65692-001LF](#)
[65781-018](#) [65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#)
[M90C108951C](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-](#)
[3052](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#) [803-41-018-10-001000](#)
[803-43-024-10-001000](#)