



Recommended P.C.B Layout(±0.05)

XKB Connectivity

Technical Data

Pin(outer sleeve):Brass,machined CuZn38Pb2

Clip(Contact 4 Finger):Beryllium copper,heat treated

Insulator:PPS UL94V-0 colour:black

Current rating:3Amps

Mating pin Ø:0.38/0.56mm

Forces:(polished steel gaugeØ0.43mm)

-Insertion:2N typ

-Withdrawal:1N typ

Mechanical life:min 500cycles

Contact resistance:max 10m Ω

Dielectric strength:min 1000V RMS

Operating temperature:-40°C to+105°C

Soldering temperature:+255°C

XKB Connectivity

X5621 F R-2xXX -C76 D32

- ①
- ②
- ③
- ④
- ⑤
- ⑥

- ① Series.N0.
- ② Category : F-Female
- ③ Welding Board Angle : R-Straight 90°
- ④ Row No-Pin No:2xXX-2x01P-2xXXP
- ⑤ Pin Length :C=7.62mm
- ⑥ Pin Length :D=3.2mm

XKB Connectivity

X5621FR-2xXX-C76D32	PPS 94V-0	Brass	Tin Gold 1u"	X5621W
PART NO	Material	Material(Terminal)	Finish(Terminal)	Mates With XKB Pin Header

					ANGULAR	±5°	DSND		DATE		SCALE: N/A	MODEL TYPE:	
Δx					≤ 4	±0.2	DWN		DATE		VIEW:	PART NO.:	
Δx					4<L≤ 16	±0.3	CHKD		DATE		UNIT: mm/in	DWG NO.:	
Δx					16<L≤ 63	±0.4	APPD		DATE		SIZE: A4	X5621FR-2xXX-C76D32	
MARK	DESCRIPTION	DATE	REVISED	APPROVED	L> 63	±0.5	UNSPECIFIED TOLERANCES			XKB INDUSTRIAL PRECISION CO.,LIMITED			
REVISIONS											WEIGHT	SHEET	REVISION
www.xk-dg.cn www.helloxkb.com www.helloxkb.cn											1.0g	1/1	A0

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [XKB](#) manufacturer:*

Other Similar products are found below :

[PJ-38647-W](#) [TC-FS66D-C-A](#) [XKNANO-1307-16](#) [X9396WR-04-N0SN](#) [X9396WR-06-N0SN](#) [X0800WRS-06HF-LPV01](#) [U221-046N-4BU02-FS](#) [X2012WR-02-N0SN](#) [X1011WVS-2x25-9TV01](#) [DC-0130-2.5A-2.0](#) [DC-0130-2.5A-2.5](#) [XKB5858-Z-F-75](#) [X2011H-05A-N0](#) [X9821H-13A-N0](#) [U263-241N-4BQC13](#) [X6511WVS-12H-C60D48R2](#) [X6511WR-10H-C30D60R2](#) [TGG.0B.P04.CLAD52H](#) [ZGG.3K.P12.CLN](#) [ZGG.3K.P12.CLL](#) [ZGG.1K.P02.CLN](#) [ZEG.2K.P02.CLL](#) [X1311FVS-02-C43D35R1](#) [ZCG.1B.P16.CLL](#) [TGG.2K.P02.CLAC50](#) [ZEG.3K.P12.CLN](#) [ZEG.2K.P12.CLN](#) [USB31-TYPE-C-FSABC](#) [X0510FVS-168AS-LPV01](#) [X0515WVS-60AS-9TV01](#) [K828801H-2x11-N0](#) [MHG.3K.P02.CLLC90H](#) [X6511FRS-05-C85D30](#) [X2001HA-PTAuN-A28B50-X2001HA-PTAuN-IDC](#) [X0709FT7BL1-A28G10-X9555H2-PTV01-IDC](#) [X2513WR-2x06A-LPSN](#) [PJ-3026](#) [TS-1101S-C-B-B-B](#) [XKB5858-Z-75](#) [SK-3390A-L1](#) [X3025WV-2x01-46SN](#) [TC-1102T-B](#) [X0800WRS-05HF-LPV01](#) [X1502WR-13K-N0SN](#) [U261-2422N-4B0178](#) [SS-3292S-L1-B](#) [X6511WR-04H-C30D60R2](#) [X9821WVS-16-9TSN](#) [X6511WR-03H-C30D60R2](#) [X1311FVS-05-C43D35R2](#)