




可定制



3(黄)
4(黑)
5(红)



1-2

200±5

3±0.5

剥线浸锡

技术要求:

- 1.1 端子铆接牢固,无松动,脱落现象;
- 1.2 线材印字清晰,无破损划伤;
- 1.3 端子与线材拉力值:≥2.5kg;
- 1.4 线材两端100%导通,无短/断路
- 1.5 外观要求按品质管理部检验标准执行
- 1.6 包装要求按包装作业指引或者客户制定包装要求

| 序号 | 线材名称 | 材料规格(符合ROHS) | 用量 | 单位 | 备注 |
|----|------|---------------------------------|-----|-----|----------------------|
| 1 | 胶壳 | GH1.25-3PJK XunPu连接器 | 1 | pcs | 打端剥皮:2.0-2.5mm |
| 2 | 端子 | GH1.25-DZ | 3 | pcs | 按照图中线序方向打端和插壳,端子与胶壳连 |
| 3 | 线材 | UL1571 28# OD0.9mm 7*0.127TS 黄色 | 200 | mm | 裁线长度:见材料表,裁线公差±2mm; |
| 4 | 线材 | UL1571 28# OD0.9mm 7*0.127TS 黑色 | 200 | mm | 裁线长度:见材料表,裁线公差±2mm; |
| 5 | 线材 | UL1571 28# OD0.9mm 7*0.127TS 红色 | 200 | mm | 裁线长度:见材料表,裁线公差±2mm; |

| | | | |
|---------------------------------------|-----------|---|------------------------------|
| MANUFACTURE DWG | |  东莞市讯普电子科技有限公司 DongGuan XunPu Electronics Co.,Ltd | |
| UNLESS OTHERWISE SPECIFIED TOLERANCES | |  | TITLE: Terminal wiring |
| | | | PAR GH125P3-157128200-111 |
| DECIMALS: | ANGLES: | | DWN |
| 0~100 ±2mm | X'.:±5° | | CHKD |
| 100~200 ±3mm | X.X':±3° | APVD | SCALE:1:1 |
| 200~300 ±5mm | X.XX':±1° | CUSTOMER COPY | UNIT:MM |
| | | SIZE:A4 | UNIT:MM |
| | | SHEET:1F1 | REV:A |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Ethernet Cables / Networking Cables](#) category:

Click to view products by [XUNPU](#) manufacturer:

Other Similar products are found below :

[73-7795-1](#) [MCJB2-10P6Q7-120](#) [84909-0204](#) [1200700174](#) [1200860368](#) [E16A06002M030](#) [E200102-009-S1](#) [AX105346-EW](#) [MT14-187L](#)
[MWDM2L-51GS-6J1-2.82B](#) [ERWPAB3002M005](#) [190-038045-01](#) [NK5EPC1GRY](#) [NK5EPC4Y](#) [1969343-6](#) [ICD056GVP163D-C0](#)
[C5UMB3FBG](#) [C631208025](#) [C631208035](#) [C6F1106015](#) [2142758-2](#) [2168427-2](#) [21949-1](#) [2J1866A](#) [RJF SFTP 5E 0500](#) [AX100351](#)
[UTPCH14GY](#) [45-5684](#) [100345-1301](#) [MWDM2L-25P-8K1-.500B](#) [MWDM6L-31S-6C4-.375H](#) [73-7793-1](#) [74764-1101](#) [WHU18-3636-048](#)
[RJF2SA2G05100BTX](#) [1R4000A39M030](#) [UTPSP6GY](#) [UTPSP2GY](#) [UTPSP10GY](#) [UTPCH5GY](#) [UTP28SP15M](#) [UTP28CH100OR](#)
[74764-2301](#) [TRD815Y-10](#) [TRD855SIG-75](#) [E66A06002M020](#) [NPC-5E-010-GY](#) [SAC-5P-MS/ 1.0-920/FS SCO AR](#) [1-3636-601-5211](#) [1-3636-600-5212](#)