



SUGGESTED PCB LAYOUT
(COMPONENT SIDE)

技术要求:

1. 塑件材料: PA66(UL-94V-0)
2. 接触件: 黄铜镀锡
3. 接触电阻: $\leq 10m\Omega$
4. 绝缘电阻: $\geq 100M\Omega$
5. 额定电压: 250V AC DC
6. 额定电流: 2.0A AC DC
7. 耐压: 能承受1000V AC/Minute
8. 工作温度: $-25^{\circ} \sim +85^{\circ}$
9. 可焊性试验: 浸锡面积 $\geq 95\%$ 温度 $235 \pm 5^{\circ}$, 时间 2.5 ± 0.5 秒
10. 铅和镉等六大有害物质含量要符合环保要求。

Part No	Pin	A	B
WAFER-HA2.54-2PZZ	2	2.50	7.50
WAFER-HA2.54-3PZZ	3	5.00	10.00
WAFER-HA2.54-4PZZ	4	7.50	12.50
WAFER-HA2.54-5PZZ	5	10.00	15.00
WAFER-HA2.54-6PZZ	6	12.50	17.50
WAFER-HA2.54-7PZZ	7	15.00	20.00
WAFER-HA2.54-8PZZ	8	17.50	22.50
WAFER-HA2.54-9PZZ	9	20.00	25.00
WAFER-HA2.54-10PZZ	10	22.50	27.50
WAFER-HA2.54-11PZZ	11	25.00	30.00
WAFER-HA2.54-12PZZ	12	27.50	32.50
WAFER-HA2.54-13PZZ	13	30.00	35.00
WAFER-HA2.54-14PZZ	14	32.50	37.50
WAFER-HA2.54-15PZZ	15	35.00	40.00
WAFER-HA2.54-16PZZ	16	37.50	42.50
WAFER-HA2.54-17PZZ	17	40.00	45.00
WAFER-HA2.54-18PZZ	18	42.50	47.50
WAFER-HA2.54-19PZZ	19	45.00	50.00
WAFER-HA2.54-20PZZ	20	47.50	52.50

2	端子Contact	黄铜	N*1	电镀(锡): 整个表面镀底镍 30u"MIN, 再镀锡80u"MIN
1	基座Wafer	PA66(UL94 V-0)	1	白色

序号	名称	材料	数量	备注
----	----	----	----	----

MANUFACTURE DWG

东莞市讯普电子科技有限公司
DongGuan XunPu Electronics Co., Ltd

UNLESS OTHERWISE SPECIFIED TOLERANCES



TITLE:
WAFER XHB2.54MM 带扣 直针

PAR WAFER-HA2.54-NPZZ

DECIMALS: ANGLES:

.X±0.20 ±2'

.XX±0.10

.XXX±0.05

CUSTOMER COPY

DWN

CHKD

APVD

SCALE:1:1 UNIT:MM

SIZE:A4 SHEET:1F1 REV:A

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [XUNPU](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [009176003701906](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#) [M90C108951C](#)
[70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [80.063.4001.1](#)
[800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#) [803-41-018-10-001000](#) [803-43-024-10-](#)
[001000](#) [803-93-012-10-001000](#)