



Part No	Pin	A	B	C	D
WAFER-MX1.25-2PZZ	2	1.25	4.40	3.20	
WAFER-MX1.25-3PZZ	3	2.50	5.65	4.45	
WAFER-MX1.25-4PZZ	4	3.75	6.90	5.70	2.50
WAFER-MX1.25-5PZZ	5	5.00	8.15	6.95	3.75
WAFER-MX1.25-6PZZ	6	6.25	9.40	8.20	5.00
WAFER-MX1.25-7PZZ	7	7.50	10.65	9.45	6.25
WAFER-MX1.25-8PZZ	8	8.75	11.90	10.70	7.50
WAFER-MX1.25-9PZZ	9	10.00	13.15	11.95	8.75
WAFER-MX1.25-10PZZ	10	11.25	14.40	13.20	10.00
WAFER-MX1.25-11PZZ	11	12.50	15.65	14.45	11.25
WAFER-MX1.25-12PZZ	12	13.75	16.90	15.70	12.50
WAFER-MX1.25-13PZZ	13	15.00	18.15	16.95	13.75
WAFER-MX1.25-14PZZ	14	16.25	19.40	18.20	15.00
WAFER-MX1.25-15PZZ	15	17.50	20.65	19.45	16.25
WAFER-MX1.25-16PZZ	16	18.75	21.90	20.70	17.50

NOTES:

- 1.BASE: LCP
- 2.PIN: Brass
- 3.Solder Tab: Brass

SPECIFICATIONS:

- 1.Spacing: 1.25
- 2.Voltage Rating: 125V AC DC
- 3.Current Rating: 1A AC DC
- 4.Insulation Resistance: 100MΩ Min
- 5.Contact Resistance: 20mΩ Max
- 6.Withstanding voltage: 500V AC 1/Minute
- 7.Temperatuer Range: $-25^{\circ} \sim + 85^{\circ}$

MANUFACTURE DWG		东莞市讯普电子科技有限公司 DongGuan XunPu Electronics Co.,Ltd	
UNLESS OTHERWISE SPECIFIED TOLERANCES			TITLE: WAFER 1.25 直针
DECIMALS: X.:±0.2			PAR WAFER-MX1.25-NPZZ
ANGLES: X'.:±5°			DWN
X.X:±0.1			CHKD
X.XX:±0.05		X.XX':±1°	APVD
CUSTOMER COPY		SCALE1:1	UNIT:MM
		SIZE:A4	UNIT:MM
		SHEET:1F1	REV:A

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [XUNPU](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [009176003701906](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [699319-000](#) [M90C108951C](#) [70.362.1628.0](#) [70-](#)
[4210](#) [70-4226B](#) [70-4853B](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [80.063.4001.1](#) [800-90-001-10-](#)
[001000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#) [803-41-018-10-001000](#) [803-43-024-10-001000](#) [803-93-012-10-001000](#) [8-1437020-4](#)
[819-22-004-30-001101](#)