



SUGGESTED PCB LAYOUT
(COMPONENT SIDE)

技术要求:

1. 塑件材料: PA66(UL-94V-0)
2. 接触件: 黄铜镀锡
3. 接触电阻: $\leq 10m\Omega$
4. 绝缘电阻: $\geq 100M\Omega$
5. 额定电压: 250V AC DC
6. 额定电流: 2.0A AC DC
7. 耐压: 能承受 1000V AC/Minute
8. 工作温度: $-25^{\circ}\sim+85^{\circ}$
9. 可焊性试验: 浸锡面积 $\geq 95\%$ 温度 $235 \pm 5^{\circ}$, 时间 2.5 ± 0.5 秒
10. 铅和镉等六大有害物质含量要符合环保要求。

Part No	Pin	A	B
WAFER-PH2.0-2PZZ	2	2.00	6.00
WAFER-PH2.0-3PZZ	3	4.00	8.00
WAFER-PH2.0-4PZZ	4	6.00	10.00
WAFER-PH2.0-5PZZ	5	8.00	12.00
WAFER-PH2.0-6PZZ	6	10.00	14.00
WAFER-PH2.0-7PZZ	7	12.00	16.00
WAFER-PH2.0-8PZZ	8	14.00	18.00
WAFER-PH2.0-9PZZ	9	16.00	20.00
WAFER-PH2.0-10PZZ	10	18.00	22.00
WAFER-PH2.0-11PZZ	11	20.00	24.00
WAFER-PH2.0-12PZZ	12	22.00	26.00
WAFER-PH2.0-13PZZ	13	24.00	28.00
WAFER-PH2.0-14PZZ	14	26.00	30.00
WAFER-PH2.0-15PZZ	15	28.00	32.00
WAFER-PH2.0-16PZZ	16	30.00	34.00
WAFER-PH2.0-17PZZ	17	32.00	36.00
WAFER-PH2.0-18PZZ	18	34.00	38.00
WAFER-PH2.0-19PZZ	19	36.00	40.00
WAFER-PH2.0-20PZZ	20	38.00	42.00

2	端子Contact	黄铜	N*1	电镀(锡): 整个表面镀底镍 30u"MIN, 再镀锡 80u"MIN
1	基座Wafer	PA66(UL94 V-0)	1	白色

序号	名称	材料	数量	备注
MANUFACTURE DWG		东莞市讯普电子科技有限公司 DongGuan XunPu Electronics Co., Ltd		
UNLESS OTHERWISE SPECIFIED TOLERANCES		TITLE: WAFER PH2.0MM 直针		
DECIMALS:		ANGLES:		PAR
.X±0.20		±2'		WAFER-PH2.0-NPZZ
.XX±0.10				DWN
.XXX±0.05				CHKD
CUSTOMER COPY		APVD SCALE 1:1 UNIT:MM SIZE: A4 SHEET: 1F1 REV: A		

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [XUNPU](#) manufacturer:

Other Similar products are found below :

[0015917161](#) [0022155065](#) [57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-](#)
[4853B](#) [71.350.2428.0](#) [733-134](#) [733-162](#) [MHR-64-VUAL](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [801-43-002-10-013000](#) [801-43-006-10-](#)
[002000](#) [803-43-024-10-001000](#) [803-93-012-10-001000](#) [8-1437020-4](#) [819-22-004-30-001101](#) [820-22-006-30-001101](#) [820-22-008-30-001101](#)
[821-22-002-10-001101](#) [821-22-003-10-002101](#)