



CODE	H	Ø	L	CODE	H	Ø	L
A1	4.3	3.5	3.15	A1	4.3	3.5	3.15
A2	4.5	3.5	3.35	A2	4.5	3.5	3.35
A3	5.0	3.5	3.85	A3	5.0	3.5	3.85
A4	5.5	3.5	4.35	A4	5.5	3.5	4.35
A5	6.0	3.5	4.85	A5	6.0	3.5	4.85
A6	6.5	3.3	5.35	A6	6.5	3.3	5.35
A7	7.0	3.3	5.85	A7	7.0	3.3	5.85
A8	7.5	3.3	6.35	A8	7.5	3.3	6.35
A9	8.0	3.3	6.85	A9	8.0	3.3	6.85
A10	8.5	3.3	7.35	A10	8.5	3.3	7.35
A11	9.0	3.1	7.85	A11	9.0	3.1	7.85
A12	9.5	3.1	8.35	A12	9.5	3.1	8.35
TOTAL HEIGHT							
CODE	H	Ø	L	CODE	H	Ø	L
A13	10	3.1	8.85	A13	10	3.1	8.85
A135	10.5	3.1	9.35	A135	10.5	3.1	9.35
A14	11	3.0	9.85	A14	11	3.0	9.85
A145	11.5	3.0	10.35	A145	11.5	3.0	10.35
A15	12	3.0	10.85	A15	12	3.0	10.85
A155	12.5	3.0	11.35	A155	12.5	3.0	11.35
A16	13	3.0	11.85	A16	13	3.0	11.85
A165	13.5	3.0	12.35	A165	13.5	3.0	12.35
A17	14	3.0	12.85	A17	14	3.0	12.85
A18	15	3.0	13.85	A18	15	3.0	13.85
A19	16	3.0	14.85	A19	16	3.0	14.85
A20	17	3.0	15.85	A20	17	3.0	15.85

OPERATING FORCE		CODE	VIGOR
B3	250±30gf	B1	120±30gf
B2	180±30gf	B2	180±30gf
B3	250±30gf	B3	250±30gf
SHRAPNEL			
CODE MATERIAL/QT		D1	C5210/1PCS
CODE MATERIAL/QT		D2	SUS/1PCS

NO.	Name	Number	Qty	Material	Remarks
⑤	Terminal		2	Brass	Silvering
④	Contact		1	SUS	Silver covered
③	Base		1	PPA	Black
②	Cover		1	SPCC	Nickel Plating
①	Knob		1	PPA	Black

YUANDI® Yuandi Electronics Co, Ltd		design	date	name	model	TS-1093A-A□B□-D□	
Review	date	Review	date	name	model	TS-1093A-A□B□-D□	
Approved	date	Approved	date	name	model	TS-1093A-A□B□-D□	
Drawing number:		Drawing number:		Drawing number:		Drawing number:	
Proportion 1:1	unit	mm	mm	mm	mm	mm	mm
Tolerance not specified		Tolerance not specified		Tolerance not specified		Tolerance not specified	
Approved	Review	Approved	Review	Approved	Review	Approved	Review
modify	modify	modify	modify	modify	modify	modify	modify
6	6	6	6	6	6	6	6
5	5	5	5	5	5	5	5
4	4	4	4	4	4	4	4
3	3	3	3	3	3	3	3
2	2	2	2	2	2	2	2
1	1	1	1	1	1	1	1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Tactile Switches](#) category:

Click to view products by [Yuandi](#) manufacturer:

Other Similar products are found below :

[KMR633NG LFG](#) [5GTH92001](#) [5GTH9202242](#) [6426-201-11343](#) [MJ1226](#) [MJTP1109B](#) [MJTP1138EAUTR](#) [MJTP1230BL](#) [MJTPSHW](#)
[GS6.90F300QP](#) [1-1977223-0](#) [1-1977120-4](#) [ADTSA62NV](#) [ADTSA62RV](#) [ADTSA63KV](#) [ADTSA644NV](#) [ADTSM24NVTR](#) [ADTSMW66NV](#)
[ADTSMW67RV](#) [ATM533VTR](#) [1571300-3](#) [B3F-3123](#) [B3F-6055A](#) [B3F-B32-01-KIT](#) [1977177-8](#) [1977266-1](#) [2-1977223-4](#) [2-1977223-7](#)
[ADTS644KV](#) [ADTSA61RV](#) [ADTSA62KV](#) [ADTSA63NV](#) [ADTSA63RV](#) [ADTSA65NV](#) [ADTSM21NSVTR](#) [ADTSM25RVTR](#)
[ADTSM31RVTR](#) [ADTSM32NVTR](#) [ADTSM61YVTR](#) [ADTSM63SVTR](#) [ADTSM644KVTR](#) [ADTSMW64RV](#) [ADTSMW69NV](#)
[FSMRA4JHA04](#) [GS4.70F300QP](#) [D38999/20JJ37SA](#) [TL1105B](#) [TL1105J](#) [ATH447K2Q](#) [ATM534VTR](#)